

SIGNAL OVERRIDE FOR SIMULATION MODELS

Cross Reference to Related Applications

5

The present application is related to the following
copending U.S. Patent Applications: U.S. Patent
Application Serial No. _____ (Docket No. AT9-98-726)
10 filed on 06/29/99, titled "Method And System For Counting
Events Within A Simulation Model"; U.S. Patent Application
Serial No. _____ (Docket No. AUS920000222US1) filed on
_____, titled "Embedded Hardware Description Language
Instrumentation"; U.S. Patent Application Serial No.
5 _____ (Docket No. AUS920000224) filed on _____,
titled "Naming And Managing Simulation Model Events"; U.S.
Patent Application Serial No. _____ (Docket No.
AUS920000225US1) filed on _____, titled "Detecting Events
Within Simulation Models"; U.S. Patent Application Serial
20 No. _____ (Docket No. AUS920000226US1) filed on
_____, titled "Randomized Simulation Model
Instrumentation"; and U.S. Patent Application Serial No.
_____ (Docket No. AUS920000228US1) filed on _____,
titled "Hierarchical Processing Of Simulation Model
Events". The above-mentioned patent applications are
25 assigned to the assignee of the present invention and are
incorporated herein by reference.

30

BACKGROUND OF THE INVENTION

1. Technical Field:

5 The present invention relates in general to designing and simulating digital devices, modules and systems. In particular, the present invention relates to a method and system that improve the model build and simulation processes in order to allow a designer to easily instrument and monitor a simulation model. More particularly, the present invention relates to overriding signals within hardware description language models during simulation.

2. Description of the Related Art:

10 Verifying the logical correctness of a digital design and debugging the design, if necessary, are very important steps in most digital design processes. Logic networks are tested either by actually building networks or by simulating networks on a computer. As logic networks become highly complex, it becomes necessary to simulate a design before the design is actually built. This is especially true when the design is implemented as an integrated circuit, since the fabrication of integrated circuits requires considerable time and correction of mistakes is quite costly. The goal of digital design simulation is the verification of the logical correctness of the design.

25 In a typical automated design process that is supported by a conventional electronic computer-aided design (ECAD) system, a designer enters a high-level

description utilizing a hardware description language (HDL), such as VHDL, producing a representation of the various circuit blocks and their interconnections. The ECAD system compiles the design description into a format that is best suited for simulation. A simulator is then utilized to verify the logical correctness of the design prior to developing a circuit layout.

A simulator is typically a software tool that operates on a digital representation, or simulation model of a circuit, and a list of input stimuli representing inputs of the digital system. A simulator generates a numerical representation of the response of the circuit which may then either be viewed on the display screen as a list of values or further interpreted, often by a separate software program, and presented on the display screen in graphical form. The simulator may be run either on a general purpose computer or on another piece of electronic apparatus specially designed for simulation. Simulators that run entirely in software on a general purpose computer will hereinafter be referred to as "software simulators". Simulators that are run with the assistance of specially designed electronic apparatus will hereinafter be referred to as "hardware simulators".

Usually, software simulators perform a very large number of calculations and operate slowly from the user's point of view. In order to optimize performance, the format of the simulation model is designed for very efficient use by the simulator. Hardware simulators, by nature, require that the simulation model comprising the circuit description be communicated in a specially designed format. In either case, a translation from an HDL description to a simulation format, hereinafter referred to as a simulation executable model, is required.

Simulation has become a very costly and time-consuming segment of the overall design process as designs become increasingly complex. Therefore, great expense is invested to ensure the highest possible accuracy and efficiency in the processes utilized to verify digital designs. A useful method of addressing design complexity is to simulate digital designs at several levels of abstraction. At the functional level, system operation is described in terms of a sequence of transactions between registers, adders, memories and other functional units. Simulation at the functional level is utilized to verify the high-level design of high-level systems.

At the logical level, a digital system is described in terms of logic elements such as logic gates and flip-flops. Simulation at the logic level is utilized to verify the correctness of the logic design. At the circuit level, each logic gate is described in terms of its circuit components such as transistors, impedances, capacitances, and other such devices. Simulation at the circuit level provides detailed information about voltage levels and switching speeds.

VHDL is a higher level language for describing the hardware design of complex devices. The overall circuit design is frequently divided into smaller parts, hereinafter referred to as design entities, which are often individually designed by different design engineers, and then combined in a hierarchical manner to create an overall model. This hierarchical design technique is very useful in managing the enormous complexity of the overall design. Another advantage of this approach is that errors in a design entity are easier to detect when that entity is simulated in isolation.

Comprehensive model verification often requires modeled signal values to be dynamically overridden during a simulation run. For example, a bus within an integrated circuit may carry signals that provide error correction values. Such error correction signals, in conjunction with bus data transmission signals, can be utilized to determine when inadvertent bus signal alterations occur due to external physical causes. An example of such an external physical cause is electrical noise near a bus signal that alters the bus signal value. Error correction signals generated at the source of the bus are examined by error correction logic at the bus destination that then corrects the error.

The simulation process includes no direct analogue to the external physical circumstances that can alter the bus signals. During simulation, error correction and bus signals are faithfully represented without inadvertent alteration.

Simulations of a given model on a simulator are typically controlled by a program, hereinafter referred to as the RTX (Run Time eXecutive), written in a high level language such as C or C++. A simulator provides interface routines that an RTX calls to control simulation. These routines implement functions for reading signal values out of a model, cycling a model, altering signals values within a model, etc.

In order to effectively simulate and verify error correction logic, a simulation run must be altered to include instructions for overriding bus signals.

Typically, an RTX calls a simulator interface routine, herein after referred to as PUTFAC, to directly alter a signal value during simulation thus injecting an error and precipitating activation of the error correction logic.

5

Using the RTX and PUTFAC to dynamically alter signals during simulation has two inherent shortcomings. First, the PUTFAC routine performs poorly on hardware simulators. Second, RTX is typically written in a high level programming language that may be unfamiliar to design engineers conversant in HDLs such as VHDL or Verilog.

10

It would therefore be useful to provide a means for altering signal values within a simulation model that is more accessible to design engineers, and furthermore, performs efficiently when utilized in conjunction with a hardware simulator.

5

SUMMARY OF THE INVENTION

A method, system, and data structure for overriding a signal during model simulation are disclosed herein.

5 An override signal port is instantiated within a model for delivering an override signal from an instrumentation entity to a signal selection means, wherein the signal selection means selects between the signal and the override signal. A signal override is declared during

10 model simulation, and in response to the declared signal override, the override signal is selected utilizing the signal selection means.

BRIEF DESCRIPTION OF THE DRAWINGS

The novel features believed characteristic of the invention are set forth in the appended claims. The invention itself, however, as well as a preferred mode of use, further objects, and advantages thereof, will best be understood by reference to the following detailed description of an illustrative embodiment when read in conjunction with the accompanying drawings, wherein:

FIG. 1 is a pictorial representation of a data processing system in which a preferred embodiment of the present invention may be practiced;

FIG. 2 depicts a representative hardware environment of the data processing system illustrated in **FIG. 1**;

FIG. 3A is a simplified block diagram illustrating a digital design entity that may be instrumented in accordance with a preferred embodiment of the present invention;

FIG. 3B is a diagrammatic representation depicting a simulation model that may be instrumental in accordance with a preferred embodiment of the present invention;

FIG. 3C is a flow diagram illustrating of a model build process in which a preferred embodiment of the present invention may be implemented;

FIG. 3D is a block diagram depicting data structures

that may be instrumental in accordance with a preferred embodiment of the present invention;

5 **FIG. 4A** is a simplified block diagram representative of an instrumentation entity utilized in a preferred embodiment of the present invention;

10 **FIG. 4B** is a simplified block diagram of a simulation model instrumented in accordance with the teachings of the present invention;

15 **FIG. 4C** illustrates exemplary sections of HDL syntax that maybe utilized in a preferred embodiment of the present invention;

20 **FIG. 4D** is a flow diagram depicting a model build process in accordance with the teachings of the present invention;

25 **FIG. 4E** is a block diagram representation of memory data structures constructed in accordance with the teachings of the present invention;

30 **FIG. 5A** is a logic diagram representation of a runtime disable mechanism in accordance with a preferred embodiment of the present invention;

35 **FIG. 5B** is a block diagram representation of functional units utilized to execute the method and system of the present invention on a hardware simulator in accordance with the teachings of the present

invention;

5 **FIG. 6A** is a simplified gate level representation of an exemplary counting instrument with a runtime disable feature and automatic clocking adjustment in accordance with the teachings of the present invention;

10 **FIG. 6B** is a simplified timing diagram illustrating automatic clocking adjustment of counting instrumentation in accordance with a preferred embodiment of the present invention;

15 **FIG. 7** depicts an alternative counting means that may be employed for counting events detected by instrumentation entities in accordance with the teachings of the present invention;

20 **FIG. 8A** illustrates a conventional finite state machine that may be instrumented with an embedded checker in accordance with the teachings of the present invention;

25 **FIG. 8B** depicts a conventional finite state machine design entity;

30 **FIG. 8C** illustrates a hardware description language file including embedded instrumentation in accordance with a preferred embodiment of the present invention; and

30 **FIG. 9** depicts a hardware description language design entity included embedded instrumentation in accordance with a preferred embodiment of the present

invention;

FIG. 10A is a block diagram illustrating a simulation model containing a number of design and instrumentation entities;

FIG. 10B depicts a data structure for declaring an event within a simulation model in accordance with one embodiment of the present invention;

FIG. 10C illustrates a list of extended event data structures for the simulation model in **FIG. 10A**;

FIG. 10D depicts a data structure for declaring an event within a simulation model in accordance with an alternate embodiment of the present invention;

FIG. 11A is a block diagram illustrating a simulation model in which the hierarchical event processing of the present invention is applicable;

FIG. 11B depicts a set of input port mapping comments for performing hierarchical processing of simulation model events in accordance with a first embodiment of the present invention;

FIG. 11C illustrates a set of input port mapping comments for performing hierarchical processing of simulation model events in accordance with a second embodiment of the present invention;

FIG. 12A depicts a representative target design

entity with an instrumentation entity containing random instrumentation logic implemented in accordance with a preferred embodiment of the present invention; and

5 **FIG. 12B** illustrates an exemplary HDL file for implementing instrumentation logic within an HDL design entity in accordance with a preferred embodiment of the present invention;

10 **FIG. 13A** depicts an exemplary design entity containing a multi-bit simulation signal;

15 **FIG. 13B** illustrates a design entity wherein signal injection is implemented in accordance with a preferred embodiment of the present invention;

20 **FIG. 13C** depicts an exemplary HDL source file that describes instrumentation entity in accordance with a preferred embodiment of the present invention; and

25 **FIG. 13D** illustrates an HDL design entity source code file wherein a set of random instrumentation comments implement the logic necessary for selectively overriding a simulation signal in accordance with a preferred embodiment of the present invention.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENT

The present invention provides for accurate and comprehensive monitoring of a digital circuit design in which a designer creates instrumentation modules utilizing the same hardware description language (HDL) as utilized for the design itself. HDLs, while suited to the needs of digital designers can also be effectively utilized for a number of checking functions. In accordance with the Method and System of the present invention, instrumentation modules are utilized to monitor specified design parameters while not becoming compiled as an integral part of the design itself. Furthermore, since the instrumentation modules are written in the same HDL as utilized in the actual design, such modules are platform and simulator independent. Unlike checking done with C or C++ programs, HDL instrumentation can be compiled and run directly without loss of performance on hardware simulators.

With reference now to the figures, and in particular with reference to **FIG. 1**, there is depicted a pictorial representation of a data processing system 10 with which the present invention may be advantageously utilized. As illustrated, data processing system 10 comprises a workstation 12 to which one or more nodes 13 are connected. Workstation 12 preferably comprises a high performance multiprocessor computer, such as the RISC System/6000 or AS/400 computer systems available from International Business Machines Corporation (IBM). Workstation 12 preferably includes nonvolatile and volatile internal storage for storing software applications comprising an ECAD system, which can be utilized to develop and verify a digital circuit design in accordance with the method and system of the present

invention. As depicted, nodes 13 are comprised of a display device 14, a keyboard 16, and a mouse 20. The ECAD software applications executed within workstation 12 preferably display a graphic user interface (GUI) within display screen 22 of display device 14 with which a digital circuit designer can interact using a keyboard 16 and mouse 20. Thus, by entering appropriate inputs utilizing keyboard 16 and mouse 20, the digital circuit designer is able to develop and verify a digital circuit design according to the method described further hereinbelow.

FIG. 2 depicts a representative hardware environment of data processing system 10. Data processing system 10 is configured to include all functional components of a computer and its associated hardware. Data processing system 10 includes a Central Processing Unit ("CPU") 24, such as a conventional microprocessor, and a number of other units interconnected via system bus 26. CPU 24 includes a portion of data processing system 10 that controls the operation of the entire computer system, including executing the arithmetical and logical functions contained in a particular computer program. Although not depicted in **FIG. 2**, CPUs such as CPU 24 typically include a control unit that organizes data and program storage in a computer memory and transfers the data and other information between the various parts of the computer system. Such CPUs also generally include an arithmetic unit that executes the arithmetical and logical operations, such as addition, comparison, multiplications and so forth. Such components and units of data processing system 10 can be implemented in a system unit such as workstation 12 of **FIG. 1**.

5 Data processing system 10 further includes random-access memory (RAM) 28, read-only memory (ROM) 30, display adapter 32 for connecting system bus 26 to display device 14, and I/O adapter 34 for connecting peripheral devices (e.g., disk and tape drives 33) to system bus 26. RAM 28 is a type of memory designed such that the location of data stored in it is independent of the content. Also, any location in RAM 28 can be accessed directly without having to work through from the beginning. ROM 30 is a type of memory that retains information permanently and in which the stored information cannot be altered by a program or normal operation of a computer.

10 Display device 14 provides the visual output of data processing system 10. Display device 14 can be a cathode-ray tube (CRT) based video display well known in the art of computer hardware. However, with a portable or notebook-based computer, display device 14 can be replaced with a liquid crystal display (LCD) based or gas plasma-based flat-panel display. Data processing system 10 further includes user interface adapter 36 for connecting keyboard 16, mouse 20, speaker 38, microphone 40, and/or other user interface devices, such as a touch-screen device (not shown), to system bus 26. Speaker 38 is one type of audio device that may be utilized in association with the method and system provided herein to assist diagnosticians or computer users in analyzing data processing system 10 for system failures, errors, and discrepancies. Communications adapter 42 connects data processing system 10 to a computer network. Although data processing system 10 is shown to contain only a single CPU and a single system bus, it should be understood that the present invention applies equally to

computer systems that have multiple CPUs and to computer systems that have multiple buses that each perform different functions in different ways.

5 Data processing system **10** also includes an interface that resides within a machine-readable media to direct the operation of data processing system **10**. Any suitable machine-readable media may retain the interface, such as RAM **28**, ROM **30**, a magnetic disk, magnetic tape, or
10 optical disk (the last three being located in disk and tape drives **33**). Any suitable operating system and associated interface (e.g., Microsoft Windows) may direct CPU **24**. For example, the AIX operating system and AIX Windows windowing system can direct CPU **24**. The AIX
15 operating system is IBM's implementation of the UNIX™ operating system. Other technologies also can be utilized in conjunction with CPU **24**, such as touch-screen technology or human voice control.

20 Those skilled in the art will appreciate that the hardware depicted in **FIG. 2** may vary for specific design and simulation applications. For example, other peripheral devices such as optical disk media, audio adapters, or chip programming devices, such as PAL or EPROM programming devices well-known in the art of
25 computer hardware and the like, may be utilized in addition to or in place of the hardware already depicted. In addition, main memory **44** is connected to system bus **26**, and includes a control program **46**. Control program **46** resides within main memory **44**, and contains
30 instructions that, when executed on CPU **24**, carries out the operations depicted in **FIG. 4D** and **FIG. 4E** described herein.

Simulated digital circuit design models are

comprised of at least one and usually many sub-units referred to hereinafter as design entities. **FIG. 3A** is a block diagram representation of an exemplary design entity **300** in which the method and system of the present invention may be implemented. Design entity **300** is defined by a number of components: an entity name, entity ports, and a representation of the function performed by design entity **300**. Each entity within a given model has a unique name (not explicitly shown in **FIG. 3A**) that is declared in the HDL description of each entity. Furthermore, each entity typically contains a number of signal interconnections, known as ports, to signals outside the entity. These outside signals may be primary input/outputs (I/Os) of an overall design or signals connecting to other entities within an overall design.

Typically, ports are categorized as belonging to one of three distinct types: input ports, output ports, and bi-directional ports. Design entity **300** is depicted in as having a number of input ports **303** that convey signals into design entity **300**. Input ports **303** are connected to input signals **301**. In addition, design entity **300** includes a number of output ports **306** that convey signals out of design entity **300**. Output ports **306** are connected to a set of output signals **304**. Bi-directional ports **305** are utilized to convey signals into and out of design entity **300**. Bi-directional ports **305** are in turn connected to a set of bi-directional signals **309**. An entity, such as design entity **300**, need not contain ports of all three types, and in the degenerate case, contains no ports at all. To accomplish the connection of entity ports to external signals, a mapping technique, known as a "port map", is utilized. A port map (not explicitly

depicted in **FIG. 3A**) consists of a specified correspondence between entity port names and external signals to which the entity is connected. When building a simulation model, ECAD software is utilized to connect external signals to appropriate ports of the entity according to a port map specification.

Finally, design entity **300** contains a body section **308** that describes one or more functions performed by design entity **300**. In the case of a digital design, body section **308** contains an interconnection of logic gates, storage elements, etc., in addition to instantiations of other entities. By instantiating an entity within another entity, a hierarchical description of an overall design is achieved. For example, a microprocessor may contain multiple instances of an identical functional unit. As such, the microprocessor itself will often be modeled as a single entity. Within the microprocessor entity, multiple instantiations of any duplicated functional entities will be present.

Referring now to **FIG. 3B**, there is illustrated a diagrammatic representation of an exemplary simulation model **329** in which a preferred embodiment of the present invention may be advantageously utilized. Simulation model **329** consists of multiple hierarchical entities. For visual simplicity and clarity, the ports and signals interconnecting the entities within simulation model **329** have not been explicitly shown. In any model, one and only one entity is the so-called "top-level entity". A top-level entity **320**, is that entity which encompasses all other entities within simulation model **329**. That is to say, top-level entity **320** instantiates, either directly or indirectly, all descendant entities within a design. Simulation model **329** consists of top-level

entity **320** which directly instantiates two instances, **321a** and **321b**, of an FXU entity **321** and a single instance of an FPU entity **322**. Each instantiation has an associated description, which contains an entity name and a unique instantiation name. For top-level entity **320**, description **310** is labeled "TOP:TOP". Description **310** includes an entity name **312**, labeled as the "TOP" preceding the colon, and also includes an instantiation name **314**, labeled as the "TOP" following the colon.

It is possible for a particular entity to be instantiated multiple times as is depicted with instantiations **321a** and **321b** of FXU entity **321**. Instantiations **321a** and **321b** are distinct instantiations of FXU entity **321** with instantiation names FXU0 and FXU1 respectively. Top-level entity **320** is at the highest level within the hierarchy of simulation model **329**. An entity that instantiates a descendant entity will be referred to hereinafter as an "ancestor" of the descendant entity. Top-level entity **320** is therefore the ancestor that directly instantiates FXU entity instantiations **321a** and **321b**. At any given level of a simulation model hierarchy, the instantiation names of all instantiations must be unique.

In addition to FXU entity instantiations **321a** and **321b**, top-level entity **320** directly instantiates a single instance of a FPU entity **322** having an entity name FPU and instantiation name FPU0. Within an entity description, it is common for the entity name to match the instantiation name when only one instance of that particular entity is placed at a given level of a simulation model hierarchy. However, this is not required as shown by entity **322** (instantiation name FPU0,

entity name FPU).

Within instantiation **321a** of FXU entity **321**, single instance entities **325a** and **326a** of entity A **325** and entity B **326** respectively, are directly instantiated. Similarly instantiation **321b** of the same FXU entity contains instantiations **325b** and **326b** of entity A **325** and entity B **326** respectively. In a similar manner, instantiation **326a** and instantiation **326b** each directly instantiate a single instance of entity C **327** as entities **327a** and **327b** respectively. The nesting of entities within other entities can continue to an arbitrary level of complexity provided that all entities instantiated, whether singly or multiply, have unique entity names and the instantiation names at any given level of the hierarchy are unique with respect to one another. Each entity is constructed from one or more HDL files that contain the information necessary to describe the entity.

Associated with each entity instantiation is a so called "instantiation identifier". The instantiation identifier for a given instantiation is a string consisting of the enclosing entity instantiation names proceeding from the top-level entity instantiation name. For example, the instantiation identifier of instantiation **327a** of entity C **327** within instantiation **321a** of FXU entity **321** is "TOP.FXU0.B.C". This identifier serves to uniquely identify each instantiation within a simulation model.

Referring now to **FIG. 3C**, there is depicted a flow diagram of a model build process in which a preferred embodiment of the present invention may be implemented. The process begins with one or more design entity HDL source code files **340** and, potentially, one or more

design entity intermediate format files 345, hereinafter referred to as "proto files" 345, available from a previous run of an HDL compiler 342. HDL compiler 342 processes HDL file(s) 340 beginning with the top level entity of a simulation model and proceeding in a recursive fashion through all HDL or proto file(s) describing a complete simulation model. For each of HDL files 340 during the compilation process, HDL compiler 342, examines proto files 345 to determine if a previously compiled proto file is available and consistent. If such a file is available and consistent, HDL compiler 342 will not recompile that particular file, but will rather refer to an extant proto file. If no such proto file is available or the proto file is not consistent, HDL compiler 342 explicitly recompiles the HDL file 340 in question and creates a proto file 344, for use in subsequent compilations. Such a process will be referred to hereinafter as "incremental compilation" and can greatly speed the process of creating a simulation executable model 348. Incremental compilation is described in further detail hereinbelow. Once created by HDL compiler 342, Proto files 344 are available to serve as proto files 345 in subsequent compilations.

In addition to proto files 344, HDL compiler 342 also creates two sets of data structures, design entity proto data structures 341 and design entity instance data structures 343, in memory 44 of computer system 10. Design entity proto data structures 341 and design entity instance data structures 343, serve as a memory image of the contents of a simulation executable model 348. Data structures 341 and 343 are passed, via memory 44, to a model build tool 346 that processes data structures 341 and 343 into simulation executable model 348.

It will be assumed hereinafter that each entity is described by a single HDL file. Depending on convention or the particular HDL in which the current invention is practiced, this restriction may be required. However, in certain circumstances or for certain HDLs it is possible to describe an entity by utilizing more than one HDL file. Those skilled in the art will appreciate and understand the extensions necessary to practice the present invention if entities are permitted to be described by multiple HDL files. Furthermore, it will be assumed that there is a direct correspondence, for each entity, between the entity name and both of the following: the name of the HDL file representing the entity, and the name of the proto file for the entity.

In the following description, an HDL source code file corresponding to a given entity will be referred to by an entity name followed by ".vhdl". For example, the HDL source code file that describes top-level entity will be referred to as TOP.vhdl. This labeling convention serves as a notational convenience only and

should not be construed as limiting the applicability of the present invention to HDLs other than VHDL.

Returning to **FIG. 3B**, it can be seen that each entity may instantiate, either directly or indirectly, one or more other entities. For example, the FXU entity directly instantiates A entity and B entity. Furthermore, B entity directly instantiates C entity. Therefore, FXU entity instantiates, directly or indirectly, A entity, B entity and C entity. Those entities, that are directly or indirectly instantiated by another entity, will be referred to hereinafter as "descendants". The descendants of top

level entity 320 are FXU entity 321, FPU entity 322, A entity 325, B entity 326, and C entity 327. It can be seen that each entity has a unique set of descendants and that each time an entity is instantiated, a unique instance of the entity and its descendants is created. Within simulation model 329, FXU entity 321 is instantiated twice, FXU:FXU0 321a and FXU:FXU1 321b, by top-level entity 320. Each instantiation of FXU entity 321 creates a unique set of instances of the FXU, A, B, and C entities.

For each entity, it is possible to define what is referred to as a "bill-of-materials" or BOM. A BOM is a list of HDL files having date and time stamps of the entity itself and the entity's descendants. Referring again to FIG. 3C, the BOM for an entity is stored in proto file 344 after compilation of the entity. Therefore, when HDL compiler 342 compiles a particular HDL source code file among HDL files 340, a proto file 344 is generated that includes a BOM listing the HDL files 340 that constitute the entity and the entity's descendants, if any. The BOM also contains the date and time stamp for each of the HDL files referenced as each appeared on disk/tape 33 of computer system 10 when the HDL file was being compiled.

If any of the HDL files constituting an entity or the entity's descendants is subsequently changed, proto file 344 will be flagged as inconsistent and HDL compiler 342 will recompile HDL file 340 on a subsequent re-compilation as will be described in further detail below. For example, going back to FIG. 3B, the HDL files referenced by the BOM of FXU entity 321 are FXU.vhdl, A.vhdl, B.vhdl and C.vhdl, each with appropriate date and

time stamps. The files referenced by the BOM of top-level entity **320** are TOP.vhdl, FXU.vhdl, A.vhdl, B.vhdl, C.vhdl, and FPU.vhdl with appropriate date and time stamps.

5

Returning to **FIG. 3C**, HDL compiler **342** creates an image of the structure of a simulation model in main memory **44** of computer system **10**. This memory image is comprised of the following components: "proto" data structures **341** and "instance" data structures **343**. A proto is a data structure that, for each entity in the model, contains information about the ports of the entity, the body contents of the entity, and a list of references to other entities directly instantiated by the entity (in what follows, the term "proto" will be utilized to refer to the in-memory data structure described above and the term "proto file" will be utilized to describe intermediate format file(s) **344**). Proto files **344** are therefore on-disk representations of the in-memory proto data structure produced by HDL compiler **342**.

10

15

20

25

30

An instance data structure is a data structure that, for each instance of an entity within a model, contains the instance name for the instance, the name of the entity the instance refers to, and the port map information necessary to interconnect the entity with external signals. During compilation, each entity will have only one proto data structure, while, in the case of multiple instantiations of an entity, each entity may have one or more instance data structures.

In order to incrementally compile a model efficiently, HDL compiler **342** follows a recursive method of compilation in which successive entities of the model

35

are considered and loaded from proto files **345** if such files are available and are consistent with the HDL source files constituting those entities and their descendants. For each entity that cannot be loaded from existing proto files **345**, HDL compiler **342** recursively examines the descendants of the entity, loads those descendant entities available from proto file(s) **345** and creates, as needed, proto files **344** for those descendants that are inconsistent with proto files **345**. Psuedocode for the main control loop of HDL compiler **342** is shown below (the line numbers to the right of the psuedocode are not a part of the psuedocode, but merely serve as a notational convenience).

```

process_HDL_file(file)                                5
{                                                       10
    if (NOT proto_loaded(file)) {                     15
        if (exists_proto_file(file) AND
            check_bom(file)) {                       20
            load_proto(file);                         25
        } else {                                     30
            parse_HDL_file(file)                     35
            for (all instances in file){              40
                process_HDL_file(instance);           45
            }                                          50
            if (design_flag = TRUE) {                 55
                for(al instrumentation instances
                    in file) {                         60
                    process_HDL_file2(instance,
                        FALSE);                       65
                }
            }                                         70
        }                                           75
        create_proto(file);                          80
        write_proto_file(file);                      90
    }                                               95
}                                                  100
if (design_flag=TRUE){                               105
    create_instance(file):                           110
}                                                  115
}                                                  120

```

When compiler **342** is initially invoked, no proto data structures **341** or instance data structures **343** are

present in memory **44** of computer system **10**. The main control loop, routine `process_HDL_file()` (line 5), is invoked and passed the name of the top level entity by means of parameter "file". The algorithm first determines if a proto data structure for the current entity is present in memory **44** by means of routine `proto_loaded()` (line 15). Note that the proto data structure for the top level entity will never be present in memory because the process starts without any proto data structures loaded into memory **44**. If a matching proto data structure is present in memory **44**, instance data structures for the current entity and the current entity's descendants, if any, are created as necessary in memory **44** by routine `create_instance()` (line 75).

However, if a matching proto data structure is not present in memory **44**, control passes to line 20 where routine `exists_proto_file()` examines proto files **345** to determine if a proto file exists for the entity. If and only if a matching proto file exists, routine `check_bom()` is called to determine whether proto file **345** is consistent. In order to determine whether the proto file is consistent, the BOM for the proto file is examined. Routine `check_bom()` examines each HDL source code file listed in the BOM to determine if the date or time stamps for the HDL source code file have changed or if the HDL source code file has been deleted. If either condition occurs for any file in the BOM, the proto file is inconsistent and routine `check_bom()` fails. However, if `check_bom()` is successful, control is passed to line 25 where routine `load_proto()` loads the proto file and any descendant proto files into memory **44**, thus creating

proto data structures **341** for the current entity and the current entity's descendants, if any. The construction of process_HDL_file() ensures that once a proto file has been verified as consistent, all of its descendant proto files, if any, are also consistent.

If the proto file is either non-existent or is not consistent, control passes to line 35 where routine parse_HDL_file() loads the HDL source code file for the current entity. Routine parse_HDL_file() (line 35) examines the HDL source code file for syntactic correctness and determines which descendant entities, if any, are instantiated by the current entity. Lines 40, 45, and 50 constitute a loop in which the routine process_HDL_file() is recursively called to process the descendent entities that are called by the current entity. This process repeats recursively traversing all the descendants of the current entity in a depth-first fashion creating proto data structures **341** and proto data files **344** of all descendants of the current entity. Once the descendant entities are processed, control passes to line 55 where a new proto data structure is created for the current entity in memory **44** by routine create_proto(). Control then passes to line 60 where a new proto file **344**, including an associated BOM, is written to disk **33** by routine write_proto_file(). Finally, control passes to line 75 where routine create_instance() creates instance data structures **343** for the current entity and any descendant entities as necessary. In this manner, process_HDL_file() (line 5) recursively processes the entire simulation model creating an in-memory image of the model consisting of

proto data structures 341 and instance data structures 343.

With reference now to **FIG. 3D** there is depicted a block diagram representing compiled data structures in which a preferred embodiment of the present invention may be implemented. Memory 44 contains proto data structures 361, one for each of the entities referred to in simulation model 329. In addition, instantiations in simulation model 329 are represented by instance data structures 362. Instance data structures 362 are connected by means of pointers indicating the hierarchical nature of the instantiations of the entities within simulation model 329. Model build tool 346 in **FIG. 3C** processes the contents of memory 44 into memory data structures in order to produce simulation executable model 348.

In order to instrument simulation models, the present invention makes use of entities known as "instrumentation entities," which are in contrast to the entities constituting a design which are referred to herein as "design entities". As with design entities, instrumentation entities are described by one or more HDL source code files and consist of a number of signal ports, a body section, and an entity name. In what follows, it will be assumed that an instrumentation entity is described by a single HDL file. Those skilled in the art will appreciate and understand extensions necessary to practice the current invention for an instrumentation entity that is described by multiple HDL

files. Each instrumentation entity is associated with a specific design entity referred to hereinafter as the "target entity".

5 With reference now to **FIG. 4A**, there is illustrated a block diagram representation of an instrumentation entity **409**. Instrumentation entity **409** includes a number of input ports **400** that are connected to signals **401** within a target entity (not depicted in **FIG. 4A**). A body section **402** contains logic necessary to detect
10 occurrences of specified conditions within the target entity and generate simulation model "events" with respect to signals **401**. A preferred embodiment of the present invention provides for generating three distinct types of events: "count" events, "fail" events, and
15 "harvest" events, each described below in turn. Body section **402** contains internal logic for detecting occurrences of conditions precipitating generation of these events. A set of multi-bit output ports **403**, **404**, and **405** are connected to external instrumentation logic
20 (depicted in **FIG. 4B**) by means of external signals **406**, **407**, and **408**. Output ports **403**, **404**, and **405** thus provide the connection from the internal logic in body section **402** to the external instrumentation logic which
25 is utilized to indicate the occurrence of count, failure and harvest events.

 A failure event is a sequence of signal values that indicate a failure in the correct operation of the simulation model. Each instrumentation entity monitors
30 the target entity for any desired number of failure events. Each occurrence of a failure event is assigned to

a particular signal bit on output port **403**. Logic within body section **402** produces an active high pulse on a specified bit of signal **403** when a failure condition is detected. Such activation of signal **403** is defined as a failure event. This error indication is conveyed by means of external signal **406** to external instrumentation logic (depicted in **FIG. 4B** as external instrumentation logic block **420**), which flags the occurrence of the failure event.

A count event is a sequence of signal values that indicate the occurrence of an event within a simulation model for which it would be advantageous to maintain a count. Count events are utilized to monitor the frequency of occurrence of specific sequences within a simulation model. Each instrumentation entity can monitor the target entity for any desired number of count events. Each count event is assigned to a particular signal bit on output port **405**. Logic block **402** contains the logic necessary to detect the occurrence of the desired count events, and in a preferred embodiment of the present invention, produces an active high pulse on the specified bit of signal **405** when a count event is detected. This count indication is conveyed by means of external signal **408** to instrumentation logic, which

contains counters utilized to record the number of occurrences of each count event.

The third event type, a harvest event, is a sequence of signal values that indicate the occurrence of a

specific operative circumstance, which would be advantageous to be able to reproduce. When a harvest event occurs, a register within an external instrumentation logic block is loaded to indicate at what point within a simulation run the event occurred, and a flag is set to indicate the occurrence of the specific circumstance. The details of the simulation run can thus be saved in order to recreate the specific circumstance monitored by the harvest event. Logic block **402** contains the logic necessary to detect the harvest events.

Each instrumentation entity can detect any desired number of harvest events that are each assigned to a particular signal bit on output port **404**. Logic within block **402** produces an active high pulse on the specified bit of signal **404** when a harvest event is detected. This harvest event detection is conveyed by means of external signal **407** to external instrumentation logic that contains a register and flag for each harvest event. The register is utilized to record at which point in the simulation run the harvest event occurred, and the flag is utilized to indicate the occurrence.

With reference now to **FIG. 4B**, wherein is depicted a block diagram representation of simulation model **329** instrumented in accordance with the teachings of the present invention. As can be seen in **FIG. 4B**, an instance **410** and an instance **411** of an instrumentation entity FXUCHK are utilized to monitor instances **321a** and **321b** of an FXU entity. For each FXU instantiations of **321a** and **321b**, an FXUCHK instantiation, **410** and **411**

respectively, is automatically generated by the mechanism of the present invention. In a similar fashion, instrumentation entity FPUCHK 412 is instantiated to monitor FPU entity 322.

5

As depicted in FIG. 4B, entity FXUCHK monitors a signals Q 372, a signal R 376, and a signal S 374 within each of instances 321a and 321b of the FXU entity. Signal Q 372, is a signal within the instances 325a and 325b of descendant entity A. Likewise, signal S 374 is a signal within descendant entity C that resides within descendant entity B. Finally, signal R 376 occurs directly within FXU entity 321. Although an instrumentation entity may monitor any signal within a target entity or the target entity's descendent entities, signals outside the target entity cannot be monitored.

10

Each instrumentation entity is connected by means of fail, count, and harvest signals to instrumentation logic block 420 containing logic for recording occurrences of each of the three event types. For the count events monitored in simulation model 329, a set of counters 421 is utilized to count the number of occurrences of each count event. In a similar manner, a set of flags 424 is utilized to record the occurrence of failure events. Finally, a set of counters 422 and flags 423 are combined and utilized to record the point at which a harvest event occurs and its occurrence, respectively. In one embodiment of the present invention, a cycle number is captured and stored utilizing counters 422 and flags 423 to record a harvest event.

25

30

To facilitate instantiation and connection of instrumentation entities, instrumentation entity HDL source code files include a specialized comment section, hereinafter referred to as "instrumentation entity description", that indicates the target entity, the signals within the target entity to be monitored, and information specifying types of events to be monitored.

With reference now to **FIG. 4C**, there is illustrated an exemplary HDL file **440** that describes instrumentation entity FXUCHK depicted in **FIG. 4B**. HDL file **440** utilizes the syntax of the VHDL hardware description language. In the VHDL language, lines beginning with two dashes, "--", are recognized by a compiler as being comments. The method and system of the present invention utilize comments of a non-conventional form to indicate information about an instrumentation entity. **FIG. 4C** depicts one embodiment of the present invention in which comments begin with two exclamation points in order to distinguish these comments from conventional comments in instrumentation HDL file **440**. It will be appreciated by those skilled in the art that the exemplary syntax utilized in **FIG. 4C** for the provision of unconventional comments is but one of many possible formats.

Within HDL file **440**, the I/O ports of a FXUCHK entity are declared in entity declaration **450**. Within entity declaration **450**, three input ports, S_IN , Q_IN , and R_IN, respectively, are declared. Input ports, S_IN , Q_IN , and R_IN, will be attached to signal S, **374**, signal Q, **372**, and signal R, **376** respectively as

described below. Input port, CLOCK, is also declared and will be connected to a signal, CLOCK, within the FXU entity. In addition, three output ports: fails (0 to 1), counts(0 to 2), and harvests(0 to 1), are declared. These output ports provide failure, count, and harvest signals for two failure events, three count events, and two harvest events. In a preferred embodiment of the present invention, the names of the output ports are fixed by convention in order to provide an efficient means for automatically connecting these signals to instrumentation logic block 420.

A set of instrumentation entity descriptors 451 are utilized to provide information about the instrumentation entity. As illustrated in FIG. 4C, descriptor comments 451 may be categorized in a number of distinct sections: prologue and entity name declaration 452, an input port map 453, a set of failure message declarations 454, a set of counter declarations 455, a set of harvest declarations 456, and an epilogue 457.

The prologue and entity name 452 serve to indicate the name of the particular target entity that the instrumentation entity will monitor. Prologue and entity name declaration 452 also serves as an indication that the instrumentation entity description has begun. Specifically, the comment "--!! Begin" within prologue and entity name 452, indicates that the description of an instrumentation entity has begun. The comment "--!! Design Entity: FXU" identifies the target entity which, in HDL file 440, is design entity FXU. In a preferred embodiment of the present invention, this declaration

serves to bind the instrumentation entity to the target entity.

Input port map **453** serves as a connection between the input ports of an instrumentation entity and the signals to be monitored within the target entity. The comments begin with comment "--!! Inputs" and end with comment "--!! End Inputs". Between these comments, comments of the form "--!! inst_ent_port_name => trgt_ent_signal_name" are utilized, one for each input port of the instrumentation entity, to indicate connections between the instrumentation entity ports and the target entity signals. The inst_ent_port_name is the name of the instrumentation entity port to be connected to the target entity signal. The trgt_ent_signal_name is the name of the signal within the target entity that will be connected to the instrumentation entity port.

In some cases a signal to be monitored lies within a descendant of a target entity. This is the case for signal S **374**, which is embedded within entity C which is a descendant of entity B **326** and target FXU entity **321**. Input port map **453** includes an identification string for signal S **374** which consists of the instance names of the entities within the target entity each separated by periods ("."). This identification string is pre-pended to the signal name. The signal mapping comment within input port map **453** for signal S **374** is therefore as follows:

```
--!! S_IN => B.C.S
```

This syntax allows an instrumentation entity to

connect to any signal within the target entity or the target entity's descendant entities. A signal appearing on the top level of the target design entity, has no prepended entity names; and therefore, has the following signal mapping comment:

```
--!! R_IN => R
```

For signals on the top level of the target entity, a special connection method is provided. If the signal to be connected to has the same name as its corresponding signal in the port map of the instrumentation entity, no input port mapping comment is required and the signal will be automatically connected if no such comment is present. In other words, if the input port mapping comment is of the form:

```
--!! signal => signal
```

where signal is a legal signal name without periods ("."), then the input port mapping comment is not required and the system of the present invention will automatically make the connect. It is also possible to provide comments of the form given above to explicitly denote the signal connection. This mechanism is only operative for signals on the top level of the target entity.

Failure message declarations **454** begin with a comment of the form "--!! Fail Outputs;", and end with a comment of the form "--!! End Fail Outputs;". Each failure event output is associated with a unique event name and a failure message. This message may be output by the simulation run-time environment upon detecting a failure event. The unique failure event name is utilized

to identify the specific failure event within the model. Each failure event signal may be declared by a comment of the form "--!! n: <eventname> "failure message";" where n is an integer denoting the failure event to which the message is associated, <eventname> is the unique failure event name, and "failure message" is the message associated with the particular failure event. One, and only one failure message declaration comment must be provided for each failure event monitored by the instrumentation entity.

Counter declaration comments **455** begin with a comment of the form "--!! Count Outputs;", and end with a comment of the form "--!! End Count Outputs;". Each count event output is associated with a unique variable name. This name is associated with a counter in counter logic **421 FIG. 4B**. The variable name provides a means to identify and reference the particular counter associated with a particular count event. Thus, a comment of the form "--!! n : <varname> qualifying_signal [+/-];" is associated with each counter event output. Within this convention, n is an integer denoting which counter event in the instrumentation module is to be associated with a variable name "varname," and qualifying_signal is the name of a signal within a target design entity utilized to determine when to sample the count event pulse as will be further described hereinbelow. The parameter "qualifying_signal" is followed by "+/-" to specify whether the qualifying signal will be a high active qualifying signal or a low active qualifying signal.

Harvest declarations **456** begin with a prologue

comment of the form "--!! Harvest Outputs;" and end with
a comment of the form "--!! End Harvest Outputs;". Each
harvest event output is associated with a unique event
name and a message that may be output by the simulation
runtime environment when a harvest event has occurred
during a simulation run. Each harvest event signal is
declared in the form "--!! n: <eventname> "harvest
message;" where n is an integer denoting which harvest
event the message is to be associated with, <eventname>
is the unique harvest event name and "harvest message" is
the message to be associated with the particular harvest
event. One, and only one, harvest message declaration
comment must be provided for each harvest event monitored
by the instrumentation entity.

Harvest messages and event names, fail messages and
event names, and counter variable names for a simulation
model are included in a simulation executable model and
lists of all the events within the model are produced in
separate files at model build time. In this manner, each
simulation model includes the information for each event
monitored and a separate file containing this information
for each event is available. Furthermore, as will be
described below, the model build process names each event
within the model (count, fail and harvest) model in such
a manner as to insure that each event has a unique name
with certain useful properties.

Finally, epilogue comment **457** consists of a single
comment of the form "--!! End;", indicating the end of
descriptor comments **451**. The remainder of
instrumentation entity HDL file **440** that follows the I/O

declarations described above, is an entity body section
458. In entity body section **458**, conventional HDL syntax
is utilized to define internal instrumentation logic
necessary to detect the various events on the input port
signals and convey these events to the output port
signals.

In addition to descriptor comments **451**, that are
located in the HDL source code file for an
instrumentation entity, an additional comment line is
required in the target entity HDL file. A comment of the
form "--!! Instrumentation: name.vhdl", where name.vhdl
is the name of the instrumentation entity HDL file, is
added to the target entity HDL source code file. This
comment provides a linkage between the instrumentation
entity and its target entity. It is possible to have
more than one such comment in a target entity when more
than one instrumentation entity is associated with the
target entity. These HDL file comments will hereinafter
be referred to as "instrumentation entity
instantiations".

With reference now to **FIG. 4D**, there is depicted a
model build process in accordance with the teachings of
the present invention. In this model build process,
instrumentation load tool **464** is utilized to alter the
in-memory proto and instance data structures of a
simulation model thereby adding instrumentation entities
to the simulation model. Instrumentation load tool **464**
utilizes descriptor comments **451** within instrumentation
HDL files **461** to create instance data structures for the
instrumentation entities within a simulation model.

The model build process of **FIG. 4D** begins with design entity HDL files **340** and, potentially, one or more design entity proto files **345** (available from a previous run of HDL compiler **462**), instrumentation entity HDL files **460**, and potentially, one or more instrumentation entity proto files **461** (available from a previous run of HDL compiler **462**). HDL compiler **462**, processes design entity HDL files **340**, and instrumentation entity HDL files **460** following an augmentation of algorithm process_HDL_file() that provides for efficient incremental compilation of the design and instrumentation entities comprising a simulation model. HDL compiler **462** loads proto data structures from design entity proto files **345** and instrumentation entity protos files **460**, if such proto files are available and consistent. If such proto files are not available or are not consistent, HDL compiler **462** compiles design entity HDL files **340** and instrumentation entity HDL files **460** in order to produce design entity proto files **344** and instrumentation entity proto files **468**. (design entity proto files **344** and instrumentation entity proto files **468** are available to serve as design entity proto files **345** and instrumentation entity proto files **460** respectively for a subsequent run of HDL compiler **462**).

In addition, HDL compiler **462** creates in-memory design proto data structures **463** and design instance data structures **465** for the design entities of a simulation model. HDL compiler **462** also creates in-memory instrumentation proto data structures **466** for the instrumentation entities of a simulation model.

In order to minimize processing overhead HDL compiler 462 neither reads nor processes descriptor comments 451. However, HDL compiler 462 does recognize instrumentation entity instantiation comments within target entity HDL files. As such, HDL compiler 462 cannot create instance data structures instrumentation entity data structures 467. The creation of instance data structures requires interconnection information contained within descriptor comments 451 not processed by HDL compiler 462. HDL compiler 462 does, however, create instrumentation proto data structures 466.

The in-memory design proto data structures 463, design instance data structures 465, and instrumentation entity proto data structures 466, are processed by instrumentation load tool 464. Instrumentation load tool 464 examines design entity proto data structures 463 and design entity instance data structures 465 to determine those design entities that are target entities. In a preferred embodiment of the present invention, this examination is accomplished by utilizing a particular comment format as previously described.

All target entities that are loaded from design entity proto files 345 contain an instantiation for any associated instrumentation entity. Therefore, instrumentation load tool 464 merely creates an instance data structure 467 for any such instrumentation entity and passes, the unaltered design proto data structure 463 to instrumented design proto data structure 463a, and passes design instance data structure 465 to instrumented

design instance data structure **465a**.

5 If however, a target entity is loaded from design
entity HDL files **340**, rather than from design entity
proto files **345**, instrumentation load tool **464** must alter
its design proto data structure **463** and its design
instance data structure **465** to instantiate an associated
instrumentation entity. An instrumented design proto
data structure **463a** and instrumented design instance data
10 structure **465a** are thereby produced. In addition,
instrumentation load tool **464** creates an instrumentation
instance data structure **467** for each instrumentation
entity associated with the current design entity.

15 The design entity proto data structures **463** that are
altered by instrumentation load tool **464** are saved to
disk **33** of computer system **10** as design entity proto
files **344**. Design entity proto files **344**, which may
include references to instrumentation entities, are
directly loaded by a subsequent compilation of a
simulation model, thus saving processing by
instrumentation load tool **464** on subsequent
recompilations unless an alteration is made to a design
entity or an associated instrumentation entity.

25 In order for HDL compiler **462** to determine if
alterations were made to either a target design entity or
the target design entity's associated instrumentation
entities, the BOM of a target design entity is expanded
30 to include the HDL files constituting the instrumentation
entities. In this manner, HDL compiler **462** can

determine, by inspection of the BOM for a given design entity, whether to recompile the design entity and the design entity's associated instrumentation entities or load these structures from proto files **345** and **461**.

5

Finally, instrumentation load tool **464** creates a unique proto and instance data structure for instrumentation logic block **420** and connects the fail, harvest, and count event signals from each instrumentation entity instantiation to instrumentation logic block **420**. Model build tool **446** processes in-memory proto and instance data structures **463a**, **465a**, **467**, **466** to produce instrumented simulation executable model **480**

10

In HDL compiler **462**, algorithm process_HDL_file() is augmented to allow for the incremental compilation of design and instrumentation entities. A pseudocode implementation of a main control loop of HDL compiler **462** is shown below:

15

20

25

30

35

```

process_HDL_file2(file, design_flag)           5
{
    if (NOT proto_loaded(file)) {               10
        if (exists_proto_file(file) AND        15
            check_bom(file)) {
            load_proto(file);                   20
        } else {
            parse_HDL_file(file)                25
        }
        for (all instances in file) {           30
            process_HDL_file2(instance,        35
                design_flag);                   40
        }
        if (design_flag = TRUE) {               45
            for (all instrumentation          50
                instances in file) {           55
                60

```

```

                                process_HDL_file2(instance,
                                FALSE);                                65
                                }                                    70
                                }                                    75
5      create_proto(file);                                80
      write_proto_file(file);                                90
      }                                    95
    }                                    100
    if (design_flag = TRUE) {                                105
10      create_instance(file);                                110
    }                                    115
  }                                    120

```

Algorithm process_HDL_file2() is an augmentation to
 15 process_HDL_file() of HDL compiler **342** in order to
 support the creation of instrumented simulation models.
 The algorithm is invoked with the name of the top level
 design entity passed through parameter file and a flag
 indicating whether the entity being processed is a design
 entity or an instrumentation entity passed through
 parameter design_flag (design_flag = TRUE for design
 entities and FALSE for instrumentation entities).
 Algorithm process_HDL_file2() (line 5) first checks, by
 means of routine proto_loaded() (line 15), if the proto
 for the current entity is already present in memory **44**.
 If so, processing passes to line **105**. Otherwise, control
 is passed to line 20 and **25** where disk **33** of computer
 system **10** is examined to determine if proto files for the
 entity and its descendants (including instrumentation
 30 entities, if any) exist and are consistent. If so, the
 appropriate proto files are loaded from disk **10** by
 routine load_proto() (line 25) creating proto data
 structures, as necessary, in memory **44** for the current
 entity and the current entity's descendants including
 35 instrumentation entities.

If the proto file is unavailable or inconsistent, control passes to line 35 where the current entity HDL file is parsed. For any entities instantiated within the current entity, lines 40 to 55 recursively call
5 process_HDL_file2() (line 5) in order to process these descendants of the current entity. Control then passes to line 55 where the design_flag parameter is examined to determine if the current entity being processed is a design entity or an instrumentation entity. If the
10 current entity is an instrumentation entity, control passes to line 80. Otherwise, the current entity is a design entity and lines 60 to 70 recursively call process_HDL_file2() (line 5) to process any instrumentation entities instantiated by means of instrumentation instantiation comments. It should be noted that algorithm process_HDL_file2() (line 5) does not allow for instrumentation entities to monitor instrumentation entities. Any instrumentation entity instantiation comments within an instrumentation entity are ignored. Control then passes to line 80 where proto data structures are created in memory 44 as needed for the current entity and any instrumentation entities. Control then passes to line 90 where the newly created proto data structures are written, as needed to disk 33
25 of computer system 10.

Control finally passes to line 105 and 110 where, if the current entity is a design entity, instance data structures are created as needed for the current entity
30 and the current entity's descendants. If the current entity is an instrumentation entity, routine create_instance() (line 110) is not called.

Instrumentation load tool **464** is utilized to create the in-memory instance data structures for instrumentation entities.

5

10

It will be apparent to those skilled in the art that HDL compiler **462** provides for an efficient incremental compilation of design and instrumentation entities. It should also be noted that the above description is but one of many possible means for accomplishing an incremental compilation of instrumentation entities. In particular, although many other options also exist, much, if not all, of the functionality of instrumentation load tool **464** can be merged into HDL compiler **462**.

15

20

25

With reference now to **FIG. 4E** wherein is shown a depiction of memory **44** at the completion of compilation of simulation model **329** with instrumentation entities FXUCHK and FPUCHK. Memory **44** contains proto data structures **481**, one for each of the design and instrumentation entities referred to in simulation model **329**. In addition, design and instrumentation instances in simulation model **329** are represented by instance data structures **482**. The instance data structures are connected by means of pointers indicating the hierarchical nature of the instantiations of the design and instrumentation entities within simulation model **329**.

25

30

With reference now to **FIG. 5A**, wherein is depicted failure flags **424** of instrumentation logic block **420** in greater detail. Failure flags **424** consist of registers

500a-500n utilized to accept and store an indication of the occurrence of a failure event. In what follows, the operation of a single failure flag for a particular failure event 502 will be discussed. The operation of all failure flags is similar.

Register 500a holds a value that represents whether a failure event 502 has occurred or not. Register 500a is initially set to a value of '0' by the simulation run-time environment at the beginning of a simulation run. When failure event 502, if enabled at register 507a, occurs, register 500a is set to a value of a logical '1', thereby indicating the occurrence of a failure event. Register 500a is driven by logical OR gate 501. Logical OR gate 501 performs a logical OR of the output of register 500a and a qualified failure signal 503 to create the next cycle value for register 500a. In this manner, once register 500a is set to a logical '1' by the occurrence of an enabled failure event, register 500a maintains the value of a logical '1' until reset by the simulation runtime environment. Likewise, register 500a maintains a value of '0' from the beginning of the simulation run until the occurrence of the failure event, if enabled.

Qualified failure signal 503 is driven by logical AND gate 505. Logical AND gate 505 produces, on qualified failure signal 503, the logical AND of failure signal 506 and the logical NOT of register 507a. Register 507a serves as an enabling control for qualified failure signal 503. If register 507a contains a value of '0', logical AND gate 505 will pass failure event signal

506 unaltered to qualified failure signal 503. In this manner, the monitoring of the failure event is enabled. Registers 507a-507n are set, by default, to a value of '0'. However, if register 507a contains a value of a logical '1', qualified failure signal 503 will remain at a value of '0' irrespective of the value of failure event signal 506, thereby disabling the monitoring of failure event 502. In this manner, register 508, consisting of registers 507a-507n, can mask the occurrence of any subset of failure events in the overall simulation model from registers 500a-500n.

To efficiently implement the ability to selectively disable the monitoring of failure events, the simulation run-time environment includes a function that allows a user to disable monitoring of a specific failure event for a given instrumentation entity. This function will automatically set the appropriate registers among registers 507a-507n within register 508 to disable the monitoring of a particular failure event for every instance of the instrumentation entity within the overall simulation model. Instrumentation load tool 464 and model build tool 446 encode sufficient information within instrumented simulation executable model 480 to determine which failure bits within register 508 correspond to which instrumentation entities.

The ability to selectively disable monitoring of failure events is of particular use in large batch-simulation environments. Typically, in such an environment, a large number of general purpose computers,

running software or hardware simulators, are dedicated to automatically running a large number of simulation runs. If a simulation model with a faulty instrumentation entity that incorrectly indicates failure events is run in such an environment, a large number of erroneous failures will be generated causing lost time. By selectively disabling failure events within instrumentation entities, the present invention allows simulation to continue while only disabling erroneous failure signals rather than having to disable all failure monitoring. This option is particularly useful when the process of correcting a faulty instrumentation entity and creating a new simulation model is substantially time consuming. The present invention also provides similar enabling and disabling structures for the harvest and count events within a model.

Logical OR gate 512 is utilized to produce a signal, 511, that indicates whether any failure event within the model has occurred. This signal is utilized to allow hardware simulators to efficiently simulate simulation models that have been instrumented according to the teachings of the present invention.

With reference now to **FIG. 5B** there is illustrated in greater detail, features of the present invention utilized to support efficient execution of an instrumented simulation model on a hardware simulator. It should be noted that for most hardware simulators, the operation of polling a facility within a simulation model during a simulation run is often a time consuming operation. In fact, if facilities must be polled every

cycle, it is often the case that as much, if not considerably more, time is spent polling a simulation model for results rather than running the actual simulation. As such, it is advantageous when using a hardware simulator to avoid polling facilities within the model during a simulation run. In addition, many hardware simulators provide a facility that instructs the hardware simulator to run a simulation without interruption until a specific signal within the simulation model attains a specific value. This facility usually results in the highest performance for a simulation run on a hardware simulator.

In order to execute simulation model 520 on a hardware simulator, a termination signal 513, is typically utilized as a means to avoid having to poll the model after each cycle. Typically, a hardware simulator will cycle simulation model 520 until signal 513 is asserted to a logical '1'. The assertion of termination signal 513 to a logical '1' indicates that a simulation run has finished. Without termination signal 513, it would be necessary to directly poll facilities within simulation model 520 to determine when a simulation run is completed.

To efficiently locate and diagnose problems in simulation model 520, it is advantageous to allow a simulation run to be stopped immediately whenever a failure event occurs during simulation of simulation model 520 (harvest events and count events are typically only polled at the end of a simulation run). This allows a user to easily locate the failure event within the

simulation run, thereby facilitating debugging of the failure. In order to allow simulation models that have been instrumented according to the teachings of the present invention to efficiently execute on a hardware simulator, a comment of the form "--!! Model Done: signalname" is placed within the HDL source code file for the top level entity of the simulation model where signalname is the name of termination signal 513 within the simulation model. This comment is only utilized if present in the HDL file for the top-level entity. If such a comment is present in the HDL source code file for the top level entity, a logical OR gate 515 will automatically be included within the simulation model. Logical OR gate 515 produces the logical OR of signals 511 and 513 on signal 516. Signal 516 is therefore asserted to a logical '1' whenever the simulation run has completed (signal 513 high) or a failure event has occurred (signal 511 high). Consequently, by executing simulation model 520 in a hardware simulator until signal 516 is asserted to a value of a logical '1', the instrumentation for simulation model 520 can be combined and utilized along with existing simulation termination techniques in a seamless manner. In the alternative, if the comment indicating the name of termination signal 513 is not present, logical OR gate 515 is not included in the model and signal 511 is directly connected to signal 516. The name of signal 516 is fixed to a particular name by convention.

In many simulators, the passage of time within the simulated model is modeled on a cycle-to-cycle basis.

That is to say, time is considered to pass in units known as cycles. A cycle is delineated by the occurrence of a clock signal within a simulation model that regulates the updating of storage elements within the design. These
5 simulators are commonly known as "cycle simulators". A cycle simulator models a digital design by repeatedly propagating the values contained within storage elements through interconnecting logic that lies between storage elements without specific regard for the physical timing
10 of this propagation, to produce next cycle values within the storage elements. In such simulators, a primitive storage element, hereinafter referred to as a "simulator latch", is utilized to model the storage elements within a digital design. One simulator cycle therefore consists of propagating the current values of the simulator
15 latches through the interconnecting logic between storage elements and updating the simulator latches with the next cycle value.

20 In many circumstances, however, it is not possible to utilize a single simulator latch to directly model the storage elements within a design. Many common storage elements utilized within digital designs often require more than one simulator latch. For example, so called
25 master-slave flip-flops are generally modeled utilizing two simulator latches to accurately simulate the behavior of such storage elements. In order to efficiently model storage elements, a designer will typically refer to a library that contains storage element simulation models
30 for use in a design. These design storage elements are modeled by one or more simulator latches. Storage

elements comprised of one or more simulator latches that are implemented within a design will be referred to hereinbelow as "design latches".

5 As a consequence of utilizing multiple simulator latches to model a design latch, the process of propagating the input of a design latch to its output, which constitutes a design cycle, often requires more than one simulator cycle. A single design cycle is thus
10 defined as comprising the number of simulator cycles required to propagate a set of values from one set of storage elements to the next.

 In other circumstances, a simulation model may consist of distinct portions that are clocked at differing frequencies. For example, a microprocessor core connected to a bus interface unit, may operate at a higher frequency and than the bus interface unit. Under these circumstances, the higher frequency portion of the design will require one or more simulator cycles, say N cycles, to simulate a single design cycle. The lower frequency portion of the design will require a multiple of N simulator cycles in order to simulate a design cycle for the lower frequency portion. This multiple is equal
20 to the ratio of the frequency of the higher speed design portion to the frequency of the lower speed design portion. It is often the case that certain portions of the logic can be run at a number of differing frequencies that are selectable at the beginning of a simulation run.
25 Such logic, with a run-time selectable frequency of
30

operation, presents unique challenges for monitoring count events.

5 With reference now to **FIG. 6A**, there is depicted a gate level representation of exemplary logic for one counter of counters **421** within instrumentation logic block **420** depicted in **FIG. 4B**. Each counter of **421** is represented by a multi-bit simulator latch **600**.

10 Simulator latch **600** is initialized by the simulation runtime environment to a value of zero at the beginning of a simulation run. Simulator latch **600** is updated every simulator cycle and is driven by multiplexor **601**. Multiplexor **601**, controlled by selector signal **602**, selects between signal **613**, the current value of simulator latch **600**, and signal **605**, the current value of simulator latch **600** incremented by 1 by incrementor **604**, to serve as the next cycle value for simulator latch **600**. By selecting signal **605**, multiplexor **601** causes the counter value within simulator latch **600** to be incremented when a count event occurs. It should be noted, however, that simulator latch **600** is updated every simulator cycle irrespective of the number of simulator cycles that correspond to a design cycle for the logic being monitored by a counting instrument. Logical AND gate **606** and simulator latch **607** serve to disable the monitoring of count event signal **609** in a manner similar to that described above for the disabling of failure events. Signal **608** is count event signal **609** further qualified by signal **610** by means of logical AND gate **611**.

25

30

Signal 610 insures that simulator latch 600 will be incremented, if count event signal 609 is active, only once per design cycle for the logic being monitored by a counting instrument irrespective of the number of simulation cycles utilized to model the design cycle. This clocking normalization is necessary to ensure that the event counts recorded in counters 421 correspond directly to the number of design cycles the event occurred in and not the number of simulator cycles the event occurred in. For example if an event occurs in two design cycles where design cycle require four simulators cycles, it is preferable to have the event counter reflect a value of two rather than a value of eight as would occur if the counter were allowed to update in every simulator cycle.

Furthermore, if the count event being monitored is within a portion of the logic with a run-time selectable frequency of operation, it is useful to have the count registers reflect the number of occurrences of the event in terms of design cycles. For example, consider a circumstance where a count event occurs twice during two different simulation runs. In the first run, assume that four simulator cycles are needed to represent each design cycle. Further assume in the second run that twelve simulator cycles are necessary to represent each design cycle. Without a clocking normalization mechanism, the first run would indicate that the event occurred eight times (two occurrences times four simulator cycles per occurrence) and the second run would indicate that the event occurred twenty-four times (two occurrences times

twelve simulator cycles per occurrence) when in fact the event actually only occurred twice in both simulation runs. Therefore, it would be advantageous to limit the updating of counters 421 such that each counter is only updated once per design cycle irrespective of the number of simulator cycles, possibly variable at run-time, needed to represent a design cycle.

In simulation models in which multiple simulator cycles are utilized to represent a single design cycle, explicit clocking signals are utilized within the model to control the updating of the various design storage elements. These clocking signals specify in which simulator cycles the simulator latches representing design storage elements are allowed to update. A clocking signal is asserted high for some contiguous number of simulator cycles either at the beginning or end of the design cycle and asserted low for the remaining simulator cycles within the design cycle. If the clocking signal is asserted high during the beginning of the design cycle, the clock is referred to as a "high-active" clock and, likewise, if the clocking signal is asserted low during the beginning of the design cycle, the clock is referred to as a "low-active" clock.

Each count event signal has an associated qualifying signal as specified by counter declaration comments 455 as described above. Typically, these qualifying signals are connected to the clocking signals within the design responsible for updating the storage elements within the

portion of logic monitored by the count event. The qualifying signal for the count event for simulator latch 600, qualifying signal 612, is depicted as a high-active qualifier signal. Qualifying signal 612 is processed by simulator latch 613 and logical AND gate 614, to produce signal 610 which is active high for one and only one simulator cycle within the design cycle delineated by qualifying signal 612.

Turning now to **FIG. 6B** there is illustrated a simplified timing diagram that demonstrates operation of simulator latch 613 and logical AND gate 614 assuming clocking qualifying signal 612 is a high active clocking signal of fifty percent duty cycle for a design cycle that occurs over a 10- simulation cycle period. Signal 615, the output of simulator latch 613, is qualifying signal 612 delayed by one simulator cycle. Signal 615 is inverted and logically ANDed with qualifying signal 612 to produce signal 610, a high-active pulse that is asserted for the first simulator cycle of the design cycle. In a similar fashion, if the qualifying clock signal is low active, qualifying signal 612 would be inverted and signal 615 would be uninverted by logical AND gate 614. This would produce a single simulator cycle active high pulse during the first simulator cycle of the design cycle. Qualifying signal 610, by qualifying count event signal 609 by means of logical AND gate 611, insures that counter 600 is incremented only once per design cycle irrespective of the number of simulator cycles utilized to represent a design cycle.

In contrast to cycle simulators, another class of simulators known as "event-driven" simulators is commonly utilized. In an event driven simulator, time is modeled in a more continuous manner. Each rising or falling edge of a signal or storage element within a design is modeled with specific regard to the physical time at which the signal transition occurred. In such simulators, the simulator latches operate in a slightly different manner than for a cycle based simulator. A simulator latch in an event driven simulator is controlled directly by a clocking signal. A new value is loaded into the simulator latch on either the rising or falling edge of the clocking signal (called a "positive-edge triggered" latch and a "negative-edge triggered" latch respectively). To practice the current invention within an event driven simulator, latch 613 and logical gates 614 and 611 are unnecessary. Rather, counter latch 600 is replaced by a positive or negative edge triggered simulator latch based on the polarity of qualifying signal 612. Qualifying signal 612 is connected directly to simulator latch 600 and directly controls the updates of counter latch 600 insuring that the latch is updated only once per design cycle.

Returning to FIG. 6A, incrementor 604 represents but one possible mechanism that may be utilized to implement the next logic state for a given counter within the present invention. As depicted in FIG. 6A, incrementor 604 ensures that counters 421 within a model are cycled

through a series of values whose binary patterns correspond to the customary representation of non-negative integers. In one embodiment of the present invention, incrementor 604 is comprised of an adder that increments the current value of counter 600 by a unit value each time signal 605 is selected by selector signal 602. This exemplary implementation provides for convenience of decoding the value of counter 600 at the termination of a simulation run, but does so at a cost in overhead that is not acceptable in many simulators.

For software simulators, one of two basic approaches may be utilized to model an incrementor, such as incrementor 604. In the first approach, the incrementor is modeled directly by an ADD or INCREMENT instruction in the simulation execution model. When incrementors are modeled directly as a single instruction within the simulation execution model, the use of incrementor 604 provides for efficient counters within a simulation execution model.

However, many software simulators and virtually all hardware simulators model incrementor functions as a set of gates that are replicated essentially without change at each bit position of the counter. Within a software simulator, these gates must be translated into a sequence of instructions. In a hardware simulator, these gates are explicitly replicated for each counter as individual gates. Due to implementation or structural limitations, many software simulators are incapable of modeling an

incrementor in any other manner than as a set of gates. Clearly, for these software simulators that must model incrementors as a number of gates and therefore as a sequence of instructions, a performance loss will result over those software simulators that model incrementors as a single increment or add instruction. Likewise, for hardware simulators, the number of gates required for each adder, which must be modeled directly by gates within the hardware simulator, can prove to be a significant burden.

The method and system of the present invention alleviate these difficulties by implementing a linear feedback shift register as the counting means within counting instrumentation. As explained below, appropriate configuration and utilization of such a linear feedback shift register results in an efficient method of incrementing a counter that avoids the overhead associated with incrementor 604.

With reference now to **FIG. 7**, there is depicted a linear feedback shift register (LFSR) counter 700 consisting of a shift register 704 and "exclusive NOR" (XNOR) gate 706. Various methods of constructing LFSRs are known to those skilled in the art. As illustrated in **FIG. 7**, LFSR counter 700 includes a modified shift register 704 that may replace register 600 and incrementor 604 of **FIG. 6A**. LFSR counter 700 also includes multiplexor 601 (replicated bit-by-bit within LFSR 704) which provide feedback paths 616. Feedback path 616 provides a means for shift register 704 to maintain its current value during those simulator cycles

in which no count pulse trigger (signal 602) is received. For hardware and software design simulators in which, for logistical or other reasons, incrementation of counters must be accomplished utilizing a set of gates for each counter, shift register 704 replaces register 600 within the counter logic depicted in FIG. 6A. The need for incrementor 604 is thus eliminated and is replaced by XNOR gate 706. In this manner, register 600 and incrementor 604 are replaced utilizing a more efficient logic structure having substantially reduced overhead. Counters 421 of FIG. 4B, will therefore consist of LFSR-based configurations such as LFSR counter 700 whose values can be decoded at the end of a simulation run to reveal their corresponding integral values.

Shift register 704 can be of any desired length. In a preferred embodiment, shift register 704 is a 22 bit register, although larger or smaller registers may be employed. Shift register 704 consists of latches 718 arranged in a serial fashion such that a given latch's output is utilized as input to the next latch 718 within shift register 704. In addition, a select subset of latches 718 within shift register 704 have their outputs sourced to XNOR gate 706. XNOR gate 706 is utilized to provide an input for the first latch within shift register 704.

The LFSR is a logic structure that, when properly configured, will sequence through all possible bit patterns with the exception of the all-ones pattern (it is possible to construct LFSRs which exclude the all-zeros pattern or LFSRs that cycle through all possible

bit patterns). For example, in a 22 bit LFSR, bits 1 and 22 may be selected for inputs to XNOR gate 706 to provide a sequence of bit patterns in shift register 704 which traverses every possible permutation with the exception of the all-ones pattern. Shift register 704 must be loaded with an initial value that is not the all ones pattern. This may be accomplished automatically by initializing all latches to a binary zero value within the simulator, or by utilizing the control program that drives the simulator to explicitly set these latches to binary zeros.

After initialization, the numeric pattern held by bit positions 718 of shift register 704 will cycle through a specific and predictable pattern in a repeating fashion. That is to say, for any given bit pattern present in shift register 704, there is a specific, unique pattern the shift register will subsequently assume upon being shifted and therefore, the sequence of patterns through which the shift register cycles is fixed and repeats in a predictable manner. Due to these properties, LFSR counter 700 can be utilized as a counting means within for the instrumentation detection means previously described. By assigning the value of "zero" to a pre-selected starting value (say the all zeros pattern for shift register 704), the value of "one" to the next bit pattern formed by shifting the LFSR, and so on, the LFSR can serve as a counter. To be useful as a counter, the bit patterns within shift register 704 must be converted back to their corresponding integer values. This is easily accomplished for LFSRs with a small number of bits (less than 25 bits) by means of a lookup table consisting of an array of values, where the index of the array corresponds to the LFSR bit pattern value and the

entry in the array is the decoded integer value for the LFSR. For LFSRs with a larger number of bits, software decoding techniques can be utilized to decode the LFSR value by simulating the operation of the LFSR.

5

10

As illustrated in **FIG. 7**, the logic necessary to implement LFSR counter **700** consists of the single XNOR gate **706** with two feedback inputs. While the number of required feedback gates and inputs thereto may vary in proportion to different possible lengths of an LFSR, in general, for typical LFSRs (less than 200 bits), only one XNOR gate with a relatively small number of inputs (less than 5 bits) is required. This is in marked contrast to the several logic gates per bit required for conventional incrementors. Therefore, significant savings in counter overhead can be achieved by substituting LFSR-based counter **700** for the incrementor structure depicted in **FIG. 6A**, especially for simulators that model incrementors utilizing logic gate based representations.

25

While the above described system and method provides a practical means of instrumenting simulation models, in certain circumstances additional techniques may be used in order to enhance the ease with which a user may instrument a simulation model. In design, it often occurs that there are common design or instrumentation logic constructs that are often repeated and possess a regular structure.

30

By utilizing knowledge of the regular structure of these design and instrumentation logic constructs, it is often possible to define a syntax that describes the instrumentation logic with considerably greater efficiency than would be possible utilizing a

conventional HDL construct. By utilizing this syntax as an unconventional HDL comment within a design VHDL file, it is possible to create instrumentation entities with considerably greater ease and efficiency.

Such comments within a design entity will be referred to hereinbelow as an embedded instrumentation entity comment while the instrumentation logic created by such a comment will be referred to as an embedded instrumentation entity.

A common logic design construct is the so-called "finite state machine". A finite state machine typically consists of a number of storage elements to maintain the "state" of the state machine and combinatorial logic that produces the next state of the state machine and its outputs. These constructs occur with great frequency in typical logic designs and it is advantageous to be able to efficiently instrument these constructs.

A typical set of count and failure events for a finite state machine includes counting the number of times a state machine cycles from a given current state to some next state, counting the number of functional cycles the state machine spends in each state, ensuring that the state machine does not enter an illegal state, and ensuring that the state machine does not proceed from a current given state to an illegal next state. This list of events is but one of many possible sets of events that can be used to characterize a finite state machine and is used in an illustrative manner only.

With reference now to **FIG. 8A** there is depicted a representation of an exemplary state machine **800**. Exemplary state machine **800** consists of five states,

labeled S0, S1, S2, S3, and S4 respectively, and nine legal state transitions between these states. In what follows, it is assumed that state machine 800 consists of three latches and a set of combinatorial logic to produce the next state function. It is further assumed that the states are encoded into the three latches following the usual and customary encoding for integers. That is to say, state S0 gets an encoding of 000_{bin} , state S1 gets an encoding of 001_{bin} , state S2 gets an encoding of 010_{bin} , and so on.

With reference now to FIG. 8B there is shown an exemplary design entity 850 referred to as entity FSM with instance name FSM, which contains one instance of state machine 800. Furthermore, a signal output 801, "fsm_state(0 to 2)" contains a three bit signal directly connected to the outputs of the three storage elements comprising the state elements of state machine 800. A signal input 802, fsm_clock, applies a clocking signal that controls the storage elements for state machine 800.

In order to instrument state machine 800, it would conventionally be necessary to create an instrumentation entity VHDL file containing the logic necessary to detect the desired state machine events and pass them through to count and fail events. Such an instrumentation entity file with appropriate instrumentation entity descriptor comments would typically require substantially more lines of code than the HDL description of the state machine itself. Such a circumstance is undesirable. However, in the case of a regular logic structure such as a finite state machine, it is possible to define a brief syntax that characterizes the finite state machine without resorting to a separate instrumentation VHDL entity.

With reference now to **FIG. 8C** there is illustrated an exemplary HDL file **860** for generating design entity **850** with an embedded instrumentation entity for monitoring the behavior of FSM **800**. Specifically, an embedded instrumentation entity comment **852** is illustrated that conforms to a preferred embodiment of the present invention. As depicted in **FIG. 8C**, embedded instrumentation entity comment **852** comprises a number of distinct sections including: a prologue and embedded instrumentation name declaration **853**, a state machine clock declaration **859**, a state element declaration **854**, a state naming declaration **855**, a state element encoding declaration **856**, a state machine arc declaration **857**, and an epilogue **858**.

Prologue and embedded instrumentation entity name declaration comment **853** serves to declare a name that is associated with this embedded instrumentation entity. This comment line also serves to delineate the beginning of an embedded instrumentation entity comment sequence.

As further depicted in **FIG. 8C**, declaration comment **853** assumes a non-conventional syntax of the form: "--!! Embedded TYPE: name", wherein "--!! Embedded" serves to declare an embedded instrumentation entity, "TYPE" declares the type of the embedded instrumentation entity - FSM in this case, and "name" is the name associated with this embedded instrumentation entity.

State machine clock declaration comment **859** is utilized to define a signal that is the clocking control for the finite state machine.

State element declaration comment **854** is utilized to

specify the state-machine state storage elements. This comment declares the storage elements or signal names that constitute the state-machine state. In state machine **800**, the signals fsm_state(0 to 2) constitute the state machine state information.

State naming declaration comment **855** is utilized to declare labels to associate with various states of the given state machine. These labels are utilized in state machine arc declaration comment **857** when defining the legal state transitions within the given state machine.

State element encoding declaration comment **856** is utilized to define a correspondence between the state machine labels defined by state naming declaration comment **855** and the facilities declared by state element declaration comment **854**. In the example shown, the labels of comment **855** are associated by position with the encodings given in comment **856** (i.e., the state labeled "S0" has the encoding 000_{bin}, the state labeled "S1" has the encoding 001_{bin}, etc.).

State-machine arc declaration comment **857** defines the legal state transitions within the state machine. The various transitions of the state machine are given by terms of the form "X => Y" where X and Y are state machine state labels given by comment **855** and X represents a previous state machine state and Y a subsequent state machine state.

Epilogue comment **858** serves to close the embedded instrumentation entity comment. The specific syntax and nature of the comments between the prologue and embedded instrumentation name declaration and the epilogue will vary with the specific needs of the type of embedded

instrumentation entity being declared.

5 Embedded instrumentation entity comment **852** is inserted within the VHDL file of the design entity that contains the finite state machine in question. The embedding of instrumentation for finite state machine **800** is made possible by the non-conventional comment syntax illustrated in **FIG. 8C** and is substantially more concise than a conventional HDL instrumentation entity suitable
10 for accomplishing the same function.

Utilizing such embedded non-conventional comments, the system of the present invention creates an instrumentation entity, as described below, for instrumenting the state machine without the need to resort to creating a separate HDL file instrumentation entity.

To support compilation and creation of embedded instrumentation entities, the previously described compilation process of **FIG. 4D** is enhanced as described herein. First, HDL compiler **462** is altered to recognize the presence of embedded instrumentation entity comments. If, during compilation of a design HDL file, and subject to the constraints described above for incremental
20 compilation, HDL compiler **462** detects one or more embedded instrumentation entity comments within the source code file, HDL compiler **462** places a special marker into design entity proto data structure **463**.
25

30 When instrumentation load tool **464** is passed control, proto data structures **463** are searched in order to locate the special marker placed by HDL compiler **462** indicating embedded instrumentation entity comments. Such protos represent the design HDL files with embedded
35

instrumentation entities that have been re-compiled in the current compilation cycle.

When instrumentation load tool **464** locates a proto data structure **463** with the special marker, the corresponding VHDL source code file for the design entity is opened and parsed to locate the one or more embedded instrumentation entity comments. For each of these comments, instrumentation load tool **464** creates a specially named proto data structure **463a**, and further generates a corresponding instance data structure **465a** that is instantiated within the design entity. In addition, instrumentation load tool **464** removes the special marker inserted by HDL compiler **462** to prevent unnecessary re-instrumentation of the design proto on subsequent re-compiles.

Within these created embedded instrumentation entity protos, instrumentation load tool **464** directly creates the necessary instrumentation logic required by the embedded instrumentation entity without the need for a VHDL file to specify this instrumentation and connects this logic to instrumentation logic block **420** of **FIG. 4D**. The updated design proto along with the embedded instrumentation entity proto and instance data structure are saved to disk and serve as inputs to subsequent compiles, removing the need to produce embedded instrumentation entities on subsequent recompiles.

With reference now to **FIG. 9**, design entity **850** is shown instrumented with embedded instrumentation entity **900** in accordance with a preferred embodiment of the present invention. Embedded instrumentation entity **900** is created as a proto instantiated within design entity **850** wherein the embedded non-conventional instrumentation

entity comment occurs. The embedded instrumentation entity thus may be replicated automatically within an overall design wherever the specific design entity is instantiated.

5

10

Embedded instrumentation entity **900** is named in a unique manner based on the name associated with the embedded instrumentation entity by the prologue and embedded instrumentation name declaration comment. This name is pre-pended with a special character (shown as a "\$" in **FIG. 9**) that is not a recognized naming convention for the platform HDL. In this manner, the names of the embedded instrumentation entities cannot conflict with the names of any other design or standard instrumentation entities.

20

25

Furthermore, the names associated with the various events defined by the embedded instrumentation entity (the "varname" for the count events, for example) are also derived in a fixed manner from the name associated with the embedded instrumentation entity. The user is required to ensure that the names of embedded instrumentation entity events do not conflict with the names of standard instrumentation entity events and further than the names of the embedded instrumentation entities within a given design do not themselves conflict.

30

35

It should also be noted that if a design entity contains more than one embedded instrumentation entity, the embedding process described with reference to **FIG. 8B** and **FIG. 9** is simply repeated for each such instrumentation entity. In addition, since the protos for the embedded instrumentation entities are created at the same time as the design protos itself, no changes to

the BOM mechanism used for incremental compiles are required. The protos for the embedded instrumentation entities can be considered, for purposes of incremental compilations, to be mere extensions to the design proto itself.

The present invention discloses a method and system for naming events within a simulation model that prevents name collisions between events in different instrumentation entities, allows for the arbitrary re-use of components of a model in models of arbitrarily increasing size, and furthermore allows for processing designated events in a hierarchical or non-hierarchical manner.

When all instances of an event are considered as a whole without regard to specific instances, the event is considered in a "non-hierarchical" sense. Likewise, when an event is considered with regard to each and every instance, it is considered in a "hierarchical" sense. When considering count events, for example, it is often convenient to track the number of times a particular count event occurred in the aggregate without concern to exactly how many times the count event occurred in each particular instance within a simulation model.

Each type of event: count, fail, and harvest, is given a separate event namespace by construction. Each event class is therefore an independent group preventing naming collisions between the event types. The data structure of the present invention is independently applied to each of the different event types to ensure correctness within each event class.

In the embodiments illustrated in Figures 10A, 10B,

10C, and 10D, the system and method of the present invention are described with respect to count events. One skilled in the art will appreciate and understand the extensions necessary to apply the same techniques to other event classes such as failures or harvests.

With reference to **FIG. 10A**, there is depicted a block diagram representation of simulation model 1000 containing a number of design and instrumentation entities. As illustrated in **FIG. 10A**, simulation model 1000 includes two instances of a design entity X, with instance names X1 and X2 respectively.

Within each of design entity instances X1 and X2 is instantiated an instance of an instrumentation entity B3, 1012a and 1012b. Design entity instances X1 and X2 further comprise instances, 1014a and 1014b, respectively, of design entity Z which further contains instances, 1016a and 1016b, of instrumentation entity B1 and instances, 1018a and 1018b, of instrumentation entity B2.

Finally, simulation model 1000 includes an instance of design entity Y, with instance name Y, containing an instance of instrumentation entity B4 1022. Design entity instance Y contains an instance, 1024, of design entity Z with further instances, 1016c and 1018c, of instrumentation entities B1 and B2 respectively.

In what follows the methods of the present invention for uniquely naming events will be considered in the context of exemplary model 1000. It will be assumed in the following description that each instrumentation entity (B1, B2, B3, and B4) has declared a single count

event with event name "count1".

5 In accordance with the method and system of the
present invention, the user must uniquely name each type
of event (count, fail, or harvest) within a specific
instrumentation entity, i.e., the user cannot declare any
two events of the same type within the same
instrumentation entity with the same event name. Such a
constraint does not conflict with the stated goals of the
10 present invention in that a given instrumentation entity
is usually created by a specific person at a specific
point in time, and maintaining unique names within such a
limited circumstance presents only a moderate burden to
the user. The data structure disclosed herein does,
however, prevent all name collisions between events in
different instrumentation entities, and allows for
processing the events in a hierarchical and/or non-
hierarchical manner.

20 As previously explained, an HDL naming convention
must uniquely identify all the entities within a given
design. This constraint is inherent to HDLs and applies
to design entities as well as instrumentation entities.
In accordance with conventional VHDL entity naming
constructs, it is technically possible for two design
25 entities to share the same entity name, *entity_name*.
However, such identically named entities must be
encapsulated within a VHDL library from which a valid
VHDL model may be constructed. In such a circumstance,
30 *entity_name*, as it is utilized herein, is equivalent to
the VHDL library name concatenated by a period (".") to
the entity name as declared in the entity declaration.

35 Pre-pending a distinct VHDL library name to the
entity name disambiguates entities sharing the same

entity name. Most HDLs include a mechanism such as this for uniquely naming each design entity. Design entities must be unambiguously named in order to determine which particular entity is called for in any given instance in a simulation model. The present invention employs the prevailing naming mechanism of the native HDL to assign unique entity names for design entities throughout a given model.

The present invention leverages this uniqueness property of entity names and the uniqueness of each instance's instantiation identifier to create an "extended event identifier" for each event within the simulation model.

With reference to **FIG. 10B**, there is illustrated a representation of the fields in an extended event identifier data structure in accordance with one embodiment of the present invention. The extended event identifier begins with instantiation identifier field **1030**. This field, as described hereinbefore, consists of the instance identifiers, proceeding from the top level entity to the direct ancestor of the given instance within the simulation model separated by periods ("."). This string is unique for each and every instance of the event within the model. The extended event identifier further includes an instrumentation entity field **1032**, a design entity field **1034**, and an eventname field **1036**.

Instrumentation entity field **1032** contains the name of the instrumentation entity (or the name assigned to an embedded instrumentation entity) that generates the simulation event. Design entity field **1034** contains the entity name of the design entity in which the event occurs. Eventname field **1036** is the name given to the

event in the instrumentation entity description comments of an instrumentation entity or the event name assigned to an event within an embedded instrumentation entity. These four namespace fields comprise a unique identifier for each event within a simulation model that allows for the re-use of components within other models without risk of name collisions and the consideration of events in a hierarchical or non-hierarchical sense.

With reference now to **FIG. 10C**, there is shown a list of extended event identifiers for model **1000**. Event identifiers **1040**, **1041**, **1042**, **1043**, **1044**, **1045**, **1046**, **1047**, and **1048** are declared within simulation model **1000** to designate count events having eventname "count1". The extended event identification procedure of the present invention will be described in the context of these extended event identifiers.

The uniqueness of the names in design entity name field **1034** is a primary distinguishing factor between events. By including the design entity name in the extended event identifier, each design entity is, in effect, given a unique namespace for the events associated with that design entity, i.e., events within a given design entity cannot have name collisions with events associated with other design entities.

It is still possible, however, to have name collisions between events defined by different instrumentation entities that are incorporated within a single design entity. Events **1041** and **1042**, for example, if identified solely by the design entity name, have a name collision. Both are events with eventname "count1" within design entity Z, and if labeled as such, are indistinguishable. In order to alleviate a naming

collision between events **1041** and **1042**, the present invention employs instrumentation entity field **1032**. By referencing the design entity and instrumentation entity names, both of which are unique with respect to themselves and each other, a unique event namespace is created for each instrumentation entity associated with any given design entity. For example, event identifier **1041** and **1042** would be in conflict (both named *Z.count1*), unless the respective instrumentation entity names are included within the extended event identifier to produce names *B1.Z.count1* and *B2.Z.count2* for these events.

It should be noted that it is possible to uniquely name each event by using instrumentation entity name field **1032** alone. Due to the uniqueness property of instrumentation entity names, event names that are only named by the instrumentation entity name and the event name field will be necessarily unique.

However, such a naming scheme is insufficient for associating events with a given design entity. In practice, it is desirable to associate events with the design entity in which they occur rather than associating them with the potentially numerous instrumentation entities that are utilized to track them. Moreover, referencing the appropriate design entity within the eventname allows all the events associated with a given design entity to be centrally referenced without the need to ascertain the names of all the instrumentation entities associated with the given design entity. The data structure of the present invention utilizes both the instrumentation entity and design entity names in naming events for ease of reference at the cost of moderate uniqueness redundancy in the event names.

In an alternative embodiment of the present invention, the instrumentation entity name is not included within the extended event identifier. Referring to **FIG. 10D**, such an alternative extended event identification data structure is depicted. As shown in **FIG. 10D**, events are named by instantiation identifier field **1030**, design entity name field **1034**, and event name field **1036**.

Such a data structure provides name collision protection between design entities but not within design entities. That is, the user must ensure that event names for events associated with a given design entity do not collide. In case of user error in this regard, model build tools may be utilized to detect an event name collision condition during model compilation. The alternative data structure depicted in **FIG. 10D** provides for simpler naming and referencing of events at the expense of requiring the user to prevent name collisions for events associated with a given design entity.

Returning to **FIG. 10B**, the combination of instrumentation entity field **1032**, design entity name field **1034**, and eventname field **1036** for a given event, provides a unique identifier for any given event without regard to multiple instantiations of the event. In order to uniquely distinguish between multiple instantiations of an event, instantiation identifier field **1030** is included in the extended event identifier. Instantiation identifier field **1030** field, by its construction, provides a unique string for any instance of an entity within any simulation model.

When evaluating occurrences of an event in a non-hierarchical sense, instantiation identifier field **1030**

is ignored while searching for matching events. As illustrated in **FIG. 10C**, for example, a non-hierarchical query for the number of time a "count1" event occurs within design entity Z as detected by instrumentation entity B1, utilizes the following list of count eventnames:

X1.Z	B1	Z	COUNT1
X2.Z	B1	Z	COUNT1
Y.Z	B1	Z	COUNT1.

These count events are added together to form an aggregate count of the total number of time the specific event occurred within the simulation model.

A hierarchical query includes specific criteria to match against the hierarchy field to limit the counter or counters found to specific instances of the requested event. For example, a query to obtain the count1 event of instrumentation entity B1 within the X1.Z instance of design entity Z utilizes the following count eventname:

X1.Z	B1	Z	COUNT1,
------	----	---	---------

which represents the number of times the count1 event was counted by instrumentation entity B1 within design entity instance X1.Z for a particular simulation interval.

By providing matching model hierarchy criteria against instantiation identifier field **1030**, it is possible to consider the events with respect to their particular instance or instances within the model, i.e., a hierarchical query. A non-hierarchical query merely ignores the hierarchy field and returns all the instances

of the requested events within the model.

With reference to **FIG. 11A**, there is depicted a block diagram illustrating a simulation model **1100** in which the hierarchical event processing of the present invention is applicable. Simulation model **1100** comprises a top-level design entity **1130** in which a pair of lower-level design entities **1102** and **1120** are instantiated. A design entity **1104** containing instrumentation entity **1106** is included within design entity **1102**. As illustrated in **FIG. 11A**, instrumentation entity **1106** includes logic **1110** for generating a simulation event **1108** from signal set **1132** from within design entity **1104**. Design entity **1120** includes an instrumentation entity **1122** that generates a simulation event **1124** using signal set **1134**.

Utilizing the techniques described hereinbefore, generating a hierarchical event that is some logical combination of events **1108** and **1124** requires the creation of an instrumentation entity associated with top level design entity **1130** that references signal sets **1132** and **1134**. Conventionally, such an instrumentation entity would substantially reproduce instrumentation logic **1110** and **1126** to process signal sets **1132** and **1134**, respectively, thus producing a copy of events **1108** and **1124**. Such a procedure is inefficient and prone to error. If, for example, changes are made to any or all of signal sets **1132** and **1134**, or instrumentation logic **1110** and **1126**, these changes would have to be accurately repeated in the instrumentation entity logic for the combined event.

The present invention provides a mechanism whereby events, such as events **1108** and **1124**, are directly referenced and utilized as inputs to cross-hierarchical instrumentation entities. In this manner, signal connections **1132** and **1134**, as well as instrumentation logic **1110** and **1126**, are directly re-utilized to produce the desired hierarchical event.

To facilitate direct referencing of events within simulation models, a specialized data structure is implemented within instrumentation entity input port map comment syntax. In accordance with a preferred embodiment of the present invention, this data structure directly connects input ports of instrumentation entities to cross-hierarchical events within a simulation model.

For the embodiment depicted in **FIG. 11A**, an instrumentation entity **1150** is instantiated within top-level design entity **1130** to generate a hierarchical event **1156** that is some function of events **1108** and **1124**. As illustrated in **FIG. 11A**, instrumentation entity **1150** includes a pair of inputs **1151** and **1152** that are directly connected to events **1124** and **1108**, respectively, utilizing the augmented syntax described below. These input connections are logically combined using instrumentation logic **1154** to produce a cross-hierarchical event **1156**.

With reference to **FIG. 11B**, there is depicted a set of input port mapping comments for performing cross-hierarchical processing of simulation model events in

accordance with the teachings of the present invention. In what follows, it is assumed that events **1108** and **1124** are count events with event names `event_1108` and `event_1124`, respectively, and that these events are connected to input ports `event_1108_in` and `event_1124_in` on instrumentation entity **1150**. As depicted in **FIG. 11B**, a first input port mapping comment **1161** contains data for referencing event **1108** to input port `event_1108_in`. A second input port mapping comment **1162** contains data for referencing event **1124** to input port `event_1124_in`. It should be noted that each of input port mapping comments **1161** and **1162** includes a pre-pended non-conventional comment identifier, `--!!`, that is utilized by the HDL compiler (such as compiler **462** in **FIG. 4D**) to maintain the port mapping comments separate from the design.

To facilitate connection of a simulation event to an instrumentation entity input port, input port mapping comments **1161** and **1162** consist of two distinct parts: an instance identifier and an event identifier. The instance identifier is a string consisting of instance names (in descending hierarchical order) of all design entities between and including the design entity containing the instrumentation entity of the cross-hierarchical event being defined (i.e., the highest level design entity for the cross-hierarchical event), and the design entity in which the event that is utilized in generating the cross-hierarchical event. If the design entity containing the hierarchical event is the same as the design entity containing the event to be connected to, the instance identifier is a null string. A pair of

instance identifiers **1163** and **1164**, within input port mapping comments **1161** and **1162**, respectively, specify that events **1124** and **1108** originate from signals within design entity **1120** and **1104** respectively.

5

Input port mapping comments **1161** and **1162** further include event identifiers **1165** and **1166**, that identify input simulation events in terms of local instrumentation entities **1106** and **1122**, respectively. In accordance with the embodiment depicted in **FIG. 11B**, each event identifier consists of a string beginning with an open bracket ("[" character and ending with a closed bracket ("]" character). Between these brackets, three sub-strings, delineated by period (".") characters, comprise a data structure utilized to identify a specific event from which the cross-hierarchical event is defined. The first sub-string within an event identifier is the instance name of the instrumentation entity containing the event. The second sub-string is a string specifying the type of the event ("count", "fail", or "harvest"). Finally, the third sub-string is the event name of the given event as specified in the declaration comment for the event. Each event identifier string uniquely identifies a single event within a given design entity. As depicted in **FIG. 11B**, event identifier strings **1165** and **1166** identify events **1108** and **1124** respectively.

10

15
20
25
30

25

30

In accordance with an alternate embodiment of the present invention, the event identifier naming structure is modified slightly for events that are labeled in accordance with **FIG. 10D** (event names that do not include

the instrumentation entity name). When an instrumentation identifier is absent from the extended event identifier, the event identifier string with an input port mapping comment consists of two sub-strings: a string denoting the type of event to connect to; and a string providing the name of the event separated by a period (".") character. The instrumentation entity name is not required in this case since all events of a given type associated with a given design entity will have unique names. The model build tools of the present invention will automatically search all instrumentation entities associated with the design entity called out by the instance identifier to determine which instrumentation entity generates an event having the name and type provided in the event identifier string.

Referring to **FIG. 11C**, there is illustrated a set of data structures for performing hierarchical processing of simulation model events in accordance with a second embodiment of the present invention. In the depicted embodiment, a pair of input port mapping comments **1171** and **1172** employ a syntax compatible with the event naming data structure depicted in **FIG. 10D**.

Input port mapping comment **1171** connects event **1108** to input port `event_1108_in` on instrumentation entity **1150**. Likewise, input port mapping comment **1172** connects event **1124** to input port `event_1124_in` on instrumentation entity **1150**. By utilizing the augmented syntax of **FIG. 11B** or **FIG. 11C** it is possible to create hierarchical events by connecting the inputs of instrumentation entities to events within the simulation model.

The above described system and method provides for practical instrumentation of simulation models and allows for efficient implementation of instrumentation logic through embedded instrumentation entities. Embedded instrumentation entities, as described hereinabove, are however necessarily limited to task-specific implementations. As described with reference to **Figures 12A and 12B**, the present invention further provides for a more flexible implementation of instrumentation logic in a more unstructured manner.

It is often necessary to tailor instrumentation logic to address unique problems and circumstances. Instrumentation logic of a specific and yet non-predefined nature that is designed in accordance with the techniques disclosed herein with reference to **Figures 12A and 12B** is referred herein as "random instrumentation logic." A data construct consisting of general logic primitives (boolean operators, storage elements, etc.) and an interconnection method for these primitives is utilized for implementing such random instrumentation logic.

For instrumenting a simulation model as described heretofore, an HDL such as VHDL or Verilog is utilized as a platform from which instrumentation logic is generated. Appropriate instrumentation entity descriptor comments within design entity source code files couple the resultant instrumentation entities to designated target design entities within a simulation model.

In addition to entity descriptor comments within a design entity source code file, the foregoing instrumentation technique requires a separate HDL file in

which the instrumentation entity is described. As explained with reference to **Figures 12A and 12B**, the present invention provides a method, system, and data structure for instrumenting design entities within a simulation model while avoiding the design process overhead required for creating a separate instrumentation entity HDL file.

In accordance with the teachings of the present invention, random instrumentation logic is directly deployed within target design entities in terms of individualized and customizable instrumentation descriptor comments. Such instrumentation descriptor comments are encoded within the target design entity HDL source code file and provide a means for the describing random instrumentation logic, events, and interconnections between the created instrumentation logic and the target design entity. The random instrumentation logic is inserted into the simulation model in a manner similar to the techniques used for embedded instrumentation entities to produce an instrumentation entity without the need for the creation of an explicit HDL instrumentation entity file.

With reference to **FIG. 12A**, there is illustrated a representative target design entity **1200** wherein random instrumentation logic is implemented in accordance with a preferred embodiment of the present invention. Instantiated within target design entity **1200** is a design entity **1201**. As further depicted in **FIG. 12A**, an instrumentation entity **1202** is instantiated within design entity **1201**. Instrumentation entity **1202** is designed in accordance with the principles set forth hereinabove to generate a count event **1203** having an event name "count1." Target design entity **1200** further includes an

instrumentation entity **1208** that is generated utilizing random instrumentation logic in accordance with a preferred embodiment of the present invention. As depicted in **FIG. 12A**, instrumentation entity **1208** receives as inputs signals *P*, *A*, *B*, and *C* along with count event **1203**.

Instrumentation entity **1208** is constructed by a set of unconventional comments lines within the source code file for target design entity **1200**. These comments may be incorporated at any point within the logic description section of the HDL source code file. HDL compiler **462** (**FIG. 4B**) recognizes the unconventional comments in addition to any comments utilized to instantiate embedded instrumentation entities within design entity **1200**. During the post-compilation/model build phase, instrumentation load tool **464** processes these comments in a manner similar to that utilized for embedded instrumentation entities (described with reference to **Figures 10A-10D**) to generate instrumentation entity **1208**.

A variety of possible syntaxes can be utilized to formulate the unconventional HDL comments required for generating random instrumentation logic within the source code file of a target design entity. As depicted in **Figure 12B**, much of the syntax of these comments employs syntax similar to the concurrent subset of the VHDL language with the addition of syntactic and semantic enhancements that provide a means of connection between an instrumentation entity and its target design entity. In addition, minor syntactic and semantic enhancements are provided to declare events and intermediate signals.

With reference now to **FIG. 12B**, there is illustrated an exemplary HDL source code file **1220** that describes design entity **1200**. Within HDL source code file **1220**, an entity instantiation **1221** produces design entity **1201**, and assignment statements **1222** are utilized to generate signals *A*, *B*, and *C*. A set of unconventional comments **1223** within HDL source code file **1220** is utilized to produce instrumentation entity **1208**. Comments **1223** are formulated as left-hand side (l.h.s.)/right-hand side (r.h.s.) assignment statements of the form:

$\{l.h.s.\} \leq \{r.h.s.\};$

where $\{l.h.s.\}$, referred to herein after as *lhs*, is the assignment statement target and, $\{r.h.s.\}$, referred to herein after as *rhs* is an expression denoting the logical value to be assigned to the statement *lhs*. A number of rules delineate the possible expressions for *lhs* and *rhs* in any legal statement in the instrumentation comments.

As employed within the instrumentation data structure of the present invention, an *lhs* statement may be either an event declaration or the name of a signal that is instantiated within an instrumentation entity. An event declaration is an expression within bracket characters ("*[*", "*]*") that generates a new event. Within comments **1223**, a statement **1230** produces a count event **1240** from instrumentation entity **1208** (**FIG. 12A**) having eventname "countname0".

Within an *lhs* event declaration, a first field

designates the event type (count, fail, harvest, etc.) and is followed by such other fields as are necessary to declare the event. As illustrated in lines 1230, 1234, and 1236, such event declaration fields follow the same format as the event declaration fields depicted in FIG. 4C.

Comments 1223 further include a line 1232 having an *lhs* that declares a signal *Q* within instrumentation entity 1208. To prevent ambiguity, any signal declared in this manner may not have a name corresponding to the name of any signal present on the top level of target design entity 1200. Conformance to this requirement is verified by instrumentation load tool 464 (FIG. 4D) during processing. Signals declared by an *lhs* expression may be incorporated within an *rhs* expression as shown in lines 1232 and 1234.

An *rhs* consists of logical connectivity expressions and/or functions that combine various signals. Signals within these connectivity expressions may originate from a number of possible sources including: signals declared on the *lhs* of a statement in the instrumentation comments; signals within the target design entity; or signals designating other events within the target design entity.

The absence of period (".") or bracket ("[", "]") characters within a signal value description in the *rhs* of a statement, designates the object signal as corresponding to either a signal within the top

hierarchical level of the target design entity or to a signal declared on the *lhs* of a statement within the instrumentation language. Signals are named in a mutually exclusive manner by the rules governing creation of signals on the *lhs* of a statement in the instrumentation comments, thereby preventing any ambiguity in the determining the source of the given signal.

Signals in *rhs* connectivity expressions can also be connections to signals within entities instantiated within the target design entity. In such a circumstance, the instance names of the entity or entities in the hierarchy enclosing the desired signal are placed before the signal name in hierarchy order, delineated by period (".") characters. For example, the signal in statement **1230** ("Y.P") represents signal **1204** within design entity **1201**. Signals at any level of the target design hierarchy are thus accessible to instrumentation logic generated by the instrumentation language comments.

Signals within the instrumentation comment expressions can also designate other events within the target entity. Event identifiers as described hereinbefore for hierarchical events are used to denote such "event" signals. For example, statement **1232** performs a logical AND of instrumentation event **1203** and signal A. The event identifier "Y.[B1.count.count1]" connects instrumentation entity **1208** to instrumentation event **1203**. This notation permits instrumentation events

at any level of design hierarchy within target design entity **1200** to be directly accessed.

As further depicted in **FIG. 12B**, statement **1232** produces intermediate signal *Q* within instrumentation entity **1208**. This is an example of an instrumentation comment statement declaring a new intermediate signal. These signals can be used in other statements to construct random instrumentation logic of any desired depth or complexity.

Statement **1234** utilizes intermediate signal *Q* along with signal **1206** to produce fail event **1241**. The syntax for fail event declaration includes a field denoting the type of event ("fail"), a field giving the event name for the fail event ("failname0"), and a final field denoting the message to associate with the fail. Finally, statement **1236** produces harvest event **1242**.

In general, the *rhs* expression of any statement in the instrumentation data structure of the present invention can access any signal or instrumentation event signal within the target design entity utilizing these syntactic mechanisms. These signals can be combined to form new events or intermediate signals that can themselves be further combined to form instrumentation logic of any desired depth or complexity.

Instrumentation comments can be placed anywhere within the logic description section of the target entity source code file. All instrumentation comments within a

file are considered as a whole and produce a single instrumentation entity within the target design entity.

It is often necessary to override signal values within a simulation model to test various functions and create certain conditions that would otherwise not be possible or simple to obtain. To provide an efficient and designer accessible means of overriding signal values within a simulation model, the present invention incorporates specialized signal override output ports and logic into instrumentation entities that permit bus signal overrides during model simulation. Such signal override output ports must have different names that the outputs for count, fail, and harvest events, and compliance with this condition is verified by instrumentation load tool 464 (FIG. 4D) during the model build process.

The signal override output ports may be declared explicitly as ports in the HDL source code file of an explicitly represented instrumentation entity. For an embedded instrumentation entity or instrumentation entities produced by random instrumentation logic comments within a target design entity, the signal override output ports are automatically generated by instrumentation load tool 464. The signal override output ports are described in output port map statements that declare an alternate value that overrides a given simulation signal. Such an output port map statement further declares the conditions under which the simulation signal will be overridden. For each simulation signal (single or multi-bit) to be overridden,

two output signals are produced: one providing the override signal value and another in the form of a single bit signal that enables or disables overriding of the simulation signal.

5 With reference to **FIG. 13A**, there is depicted an exemplary HDL design entity **1300** containing a multi-bit simulation signal *R*. Simulation signal *R* is driven by one or more sources within a logic module **1302**, and is
10 received by one or more sinks within a logic module **1304**. While the present invention will be described with respect to overriding signal *R*, one skilled in the art will understand and appreciate the extensions necessary to apply the principles set forth herein to overriding single bit signals or subsets of multi-bit signals.

Referring to **FIG. 13B**, signal override functionality is incorporated within design entity **1300** in accordance with a preferred embodiment of the present invention. As illustrated in **FIG. 13B**, design entity **1300** includes an instrumentation entity **1306** that is equipped to override signal *R*. In the depicted embodiment, instrumentation entity **1306** produces a signal *R_OV*(0..4) that is utilized within HDL design entity **1300** to selectively replace
25 signal *R* as an input into logic module **1304**. Instrumentation entity **1306** further produces a signal *RT* that enables an override of signal *R* with signal *R_OV*(0..4).

30 During a model build process, instrumentation load tool **464**, instantiates a multiplexor (MUX) **1308** that breaks the path of the original signal *R* as depicted in

FIG. 13A to produce signal R' that is input into logic module **1304**. MUX **1308** is directly instantiated by instrumentation load tool **464** into the design proto data structure for instrumentation entity **1306** without the need to alter the HDL source code for HDL design entity **1300**. MUX **1308** selects between override signal $R_OV(0..4)$ and the original signal value R to determine the value of signal R' .

MUX **1308** is controlled by a select signal **1310** that is driven by logical AND gate **1312**. Logical AND gate **1312** is driven by signal RT and a latch bit signal from a latch **1314**. In a manner similar to that described in relation fail events in **FIG. 5A**, latch **1314**, when loaded with a binary '1' value, forces MUX **1308** to select the original signal value R , thereby disabling overrides of signal R .

Instrumentation load tool **464** generates latch **1314** and logical AND gate **1312** for every overriddable signal within the simulation model. All signal overrides within a model can thus be selectively and individually disabled. For each overriddable signal, latch **1314** resides within instrumentation logic block **420** as depicted in **FIG. 4B**. In accordance with a preferred embodiment, only one instrumentation entity may override a given single bit signal or any signal or subset of signals within a multi-bit signal.

The signal override system of the present invention further provides a means by which instrumentation

entities may access the original unaltered version of any given signal within the simulation model. As depicted in **FIG. 13B**, for example, instrumentation entity **1306** accesses the unaltered signal *R* by means of input signal **1320**.

With reference to **FIG. 13C**, there is illustrated an exemplary HDL source code file **1340** that describes instrumentation entity **1306** in accordance with a preferred embodiment of the present invention. HDL source code file **1340** includes entity descriptor comments **1351** and an architecture section **1358** comprising the functional logic within instrumentation entity **1306**.

Within HDL source code file **1340**, an input port map statement **1364** declares an input port **1309** at which instrumentation entity **1306** receives signal *R* from logic module **1302**. A set of output port map statements **1362** and **1363** define the output ports from instrumentation entity **1306** for signals *R_OV(0..4)* and *RT*, respectively.

An input port map comment **1360** connects signal input **1320** to instrumentation entity **1306**. Input port map comment **1360** employs an augmented syntax from that previously described for input port map comments. Signals that appear within brace ("{" , "}") characters are defined to reference the original unaltered version of a signal within a particular target design entity. Hence the statement

```
--!! R_IN(0 to 4) => {R(0 to 4)}
```

connects input port *R_IN* to signal *R* in the altered design proto data structure. The brace syntax may be used to enclose any signal within a port map comment or any signal referred to within a random instrumentation comment statement RHS. If a signal referenced within braces has no associated override mechanism in the model, the signal declaration within braces merely resolves to the unaltered signal itself.

An additional comment section, output declarations **1361**, is further included within the descriptor comment syntax to declare signal overrides. Output declaration comment **1361** serves to generate the override logic shown in **FIG. 13B** and connect signals *RT* and *R_OV(0..4)* to the override logic. Output declarations such as output declaration comment **1361** are of the form:

```
--!! <name> : out_port => target_signal [ctrl_port];
```

where *name* is a name associated with the specific signal override (*R_OVERRIDE* in **FIG. 13C**), *out_port* is the output port providing the override value for the signal, *target_signal* is the name of the signal to be overridden, and *ctrl_port* is the single bit output port that determines when the target signal is overridden.

One such output declaration is required for every overridable signal. Signals designated by *out_port* and *ctrl_port* must appear as outputs declared in the HDL port map for the entity. As it does for instrumentation entities, instrumentation load tool **464** parses the comments depicted in **FIG. 13C** and alters the proto data

structures within the simulation model at model build time to produce a result such as that depicted in **FIG. 13B**.

5 Furthermore, each signal override is given a unique name based on the "name" field within the output declaration comment in a manner analogous to that described earlier for count events. In this manner, each signal override can be specifically referred to for such
10 purposes as disabling the signal override by setting latch 1314 as shown in **FIG. 13B**.

While **FIG. 13C** illustrates only those constructs necessary for implementing a signal override, it should be noted that there is no limitation placed upon the creation of count, fail, and harvest events within the same instrumentation entity as a signal override, and furthermore, that multiple signal override entities may be incorporated within the same instrumentation entity.

Referring to **FIG. 13D**, there is depicted an HDL source code file for producing design entity 1300 wherein a set of random instrumentation comments 1380 implement the logic necessary for selectively overriding signal R. A comment 1381 connects the unaltered version of signal R
25 (referred to within the braces ("{" , "}") syntax) to an internal instrumentation signal R_IN. A pair of comments 1382 and 1383 assign values for signals R_OV and RT (the exact expressions assigned to RT and R_OV are not depicted). An event declaration instrumentation comment
30 1384 produces a signal that enables signal R to be

overridden.

In accordance with the depicted embodiment, an event declaration comment is of the form:

[override, <name>, <target_signal>, <ctrl_signal>]

where override is a fixed string denoting a signal override, "<name>" is the name assigned to the override, "<target_signal>" is the name of the signal in the target entity to be altered, and "<ctrl_signal>" is the name of the signal that determines when the signal override takes effect. By utilizing random instrumentation comments, a design engineer can efficiently create signal overrides.

Since, in accordance with the teachings of the present invention, signal overrides are implemented directly using hardware constructs, it is possible to efficiently utilize signal overrides within a hardware simulator.

While the invention has been particularly shown as described with reference to a preferred embodiment, it will be understood by those skilled in the art that various changes in form and detail may be made therein without departing from the spirit and scope of the invention. One of the embodiments of the invention can be implemented as sets of instructions resident in random access memory 28 of one or more computer systems configured generally as described in FIG. 1 and FIG. 2. Until required by computer system 10, the set of instructions may be stored in another computer readable storage device, such as disk drive 33 or in a removable

storage device such as an optical disk for eventual use
in a CD-ROM drive or a floppy disk for eventual use in a
floppy disk drive. The set of instructions may be
referred to as a computer program product. Further, the
5 set of instructions can be stored in the memory of
another computer and transmitted over a local area
network or a wide area network, such as the Internet,
when desired by the user. It is therefore contemplated
that such modifications can be made without departing
10 from the spirit or scope of the present invention as
defined in the appended claims.

11 12 13 14 15 16 17 18 19 20 21 22 23 24 25 26 27 28 29 30 31 32 33 34 35 36 37 38 39 40 41 42 43 44 45 46 47 48 49 50 51 52 53 54 55 56 57 58 59 60 61 62 63 64 65 66 67 68 69 70 71 72 73 74 75 76 77 78 79 80 81 82 83 84 85 86 87 88 89 90 91 92 93 94 95 96 97 98 99 100 101 102 103 104 105 106 107 108 109 110 111 112 113 114 115 116 117 118 119 120 121 122 123 124 125 126 127 128 129 130 131 132 133 134 135 136 137 138 139 140 141 142 143 144 145 146 147 148 149 150 151 152 153 154 155 156 157 158 159 160 161 162 163 164 165 166 167 168 169 170 171 172 173 174 175 176 177 178 179 180 181 182 183 184 185 186 187 188 189 190 191 192 193 194 195 196 197 198 199 200 201 202 203 204 205 206 207 208 209 210 211 212 213 214 215 216 217 218 219 220 221 222 223 224 225 226 227 228 229 230 231 232 233 234 235 236 237 238 239 240 241 242 243 244 245 246 247 248 249 250 251 252 253 254 255 256 257 258 259 260 261 262 263 264 265 266 267 268 269 270 271 272 273 274 275 276 277 278 279 280 281 282 283 284 285 286 287 288 289 290 291 292 293 294 295 296 297 298 299 300 301 302 303 304 305 306 307 308 309 310 311 312 313 314 315 316 317 318 319 320 321 322 323 324 325 326 327 328 329 330 331 332 333 334 335 336 337 338 339 340 341 342 343 344 345 346 347 348 349 350 351 352 353 354 355 356 357 358 359 360 361 362 363 364 365 366 367 368 369 370 371 372 373 374 375 376 377 378 379 380 381 382 383 384 385 386 387 388 389 390 391 392 393 394 395 396 397 398 399 400 401 402 403 404 405 406 407 408 409 410 411 412 413 414 415 416 417 418 419 420 421 422 423 424 425 426 427 428 429 430 431 432 433 434 435 436 437 438 439 440 441 442 443 444 445 446 447 448 449 450 451 452 453 454 455 456 457 458 459 460 461 462 463 464 465 466 467 468 469 470 471 472 473 474 475 476 477 478 479 480 481 482 483 484 485 486 487 488 489 490 491 492 493 494 495 496 497 498 499 500 501 502 503 504 505 506 507 508 509 510 511 512 513 514 515 516 517 518 519 520 521 522 523 524 525 526 527 528 529 530 531 532 533 534 535 536 537 538 539 540 541 542 543 544 545 546 547 548 549 550 551 552 553 554 555 556 557 558 559 560 561 562 563 564 565 566 567 568 569 570 571 572 573 574 575 576 577 578 579 580 581 582 583 584 585 586 587 588 589 590 591 592 593 594 595 596 597 598 599 600 601 602 603 604 605 606 607 608 609 610 611 612 613 614 615 616 617 618 619 620 621 622 623 624 625 626 627 628 629 630 631 632 633 634 635 636 637 638 639 640 641 642 643 644 645 646 647 648 649 650 651 652 653 654 655 656 657 658 659 660 661 662 663 664 665 666 667 668 669 670 671 672 673 674 675 676 677 678 679 680 681 682 683 684 685 686 687 688 689 690 691 692 693 694 695 696 697 698 699 700 701 702 703 704 705 706 707 708 709 710 711 712 713 714 715 716 717 718 719 720 721 722 723 724 725 726 727 728 729 730 731 732 733 734 735 736 737 738 739 740 741 742 743 744 745 746 747 748 749 750 751 752 753 754 755 756 757 758 759 760 761 762 763 764 765 766 767 768 769 770 771 772 773 774 775 776 777 778 779 780 781 782 783 784 785 786 787 788 789 790 791 792 793 794 795 796 797 798 799 800 801 802 803 804 805 806 807 808 809 810 811 812 813 814 815 816 817 818 819 820 821 822 823 824 825 826 827 828 829 830 831 832 833 834 835 836 837 838 839 840 841 842 843 844 845 846 847 848 849 850 851 852 853 854 855 856 857 858 859 860 861 862 863 864 865 866 867 868 869 870 871 872 873 874 875 876 877 878 879 880 881 882 883 884 885 886 887 888 889 890 891 892 893 894 895 896 897 898 899 900 901 902 903 904 905 906 907 908 909 910 911 912 913 914 915 916 917 918 919 920 921 922 923 924 925 926 927 928 929 930 931 932 933 934 935 936 937 938 939 940 941 942 943 944 945 946 947 948 949 950 951 952 953 954 955 956 957 958 959 960 961 962 963 964 965 966 967 968 969 970 971 972 973 974 975 976 977 978 979 980 981 982 983 984 985 986 987 988 989 990 991 992 993 994 995 996 997 998 999 1000 1001 1002 1003 1004 1005 1006 1007 1008 1009 1010 1011 1012 1013 1014 1015 1016 1017 1018 1019 1020 1021 1022 1023 1024 1025 1026 1027 1028 1029 1030 1031 1032 1033 1034 1035 1036 1037 1038 1039 1040 1041 1042 1043 1044 1045 1046 1047 1048 1049 1050 1051 1052 1053 1054 1055 1056 1057 1058 1059 1060 1061 1062 1063 1064 1065 1066 1067 1068 1069 1070 1071 1072 1073 1074 1075 1076 1077 1078 1079 1080 1081 1082 1083 1084 1085 1086 1087 1088 1089 1090 1091 1092 1093 1094 1095 1096 1097 1098 1099 1100 1101 1102 1103 1104 1105 1106 1107 1108 1109 1110 1111 1112 1113 1114 1115 1116 1117 1118 1119 1120 1121 1122 1123 1124 1125 1126 1127 1128 1129 1130 1131 1132 1133 1134 1135 1136 1137 1138 1139 1140 1141 1142 1143 1144 1145 1146 1147 1148 1149 1150 1151 1152 1153 1154 1155 1156 1157 1158 1159 1160 1161 1162 1163 1164 1165 1166 1167 1168 1169 1170 1171 1172 1173 1174 1175 1176 1177 1178 1179 1180 1181 1182 1183 1184 1185 1186 1187 1188 1189 1190 1191 1192 1193 1194 1195 1196 1197 1198 1199 1200 1201 1202 1203 1204 1205 1206 1207 1208 1209 1210 1211 1212 1213 1214 1215 1216 1217 1218 1219 1220 1221 1222 1223 1224 1225 1226 1227 1228 1229 1230 1231 1232 1233 1234 1235 1236 1237 1238 1239 1240 1241 1242 1243 1244 1245 1246 1247 1248 1249 1250 1251 1252 1253 1254 1255 1256 1257 1258 1259 1260 1261 1262 1263 1264 1265 1266 1267 1268 1269 1270 1271 1272 1273 1274 1275 1276 1277 1278 1279 1280 1281 1282 1283 1284 1285 1286 1287 1288 1289 1290 1291 1292 1293 1294 1295 1296 1297 1298 1299 1300 1301 1302 1303 1304 1305 1306 1307 1308 1309 1310 1311 1312 1313 1314 1315 1316 1317 1318 1319 1320 1321 1322 1323 1324 1325 1326 1327 1328 1329 1330 1331 1332 1333 1334 1335 1336 1337 1338 1339 1340 1341 1342 1343 1344 1345 1346 1347 1348 1349 1350 1351 1352 1353 1354 1355 1356 1357 1358 1359 1360 1361 1362 1363 1364 1365 1366 1367 1368 1369 1370 1371 1372 1373 1374 1375 1376 1377 1378 1379 1380 1381 1382 1383 1384 1385 1386 1387 1388 1389 1390 1391 1392 1393 1394 1395 1396 1397 1398 1399 1400 1401 1402 1403 1404 1405 1406 1407 1408 1409 1410 1411 1412 1413 1414 1415 1416 1417 1418 1419 1420 1421 1422 1423 1424 1425 1426 1427 1428 1429 1430 1431 1432 1433 1434 1435 1436 1437 1438 1439 1440 1441 1442 1443 1444 1445 1446 1447 1448 1449 1450 1451 1452 1453 1454 1455 1456 1457 1458 1459 1460 1461 1462 1463 1464 1465 1466 1467 1468 1469 1470 1471 1472 1473 1474 1475 1476 1477 1478 1479 1480 1481 1482 1483 1484 1485 1486 1487 1488 1489 1490 1491 1492 1493 1494 1495 1496 1497 1498 1499 1500 1501 1502 1503 1504 1505 1506 1507 1508 1509 1510 1511 1512 1513 1514 1515 1516 1517 1518 1519 1520 1521 1522 1523 1524 1525 1526 1527 1528 1529 1530 1531 1532 1533 1534 1535 1536 1537 1538 1539 1540 1541 1542 1543 1544 1545 1546 1547 1548 1549 1550 1551 1552 1553 1554 1555 1556 1557 1558 1559 1560 1561 1562 1563 1564 1565 1566 1567 1568 1569 1570 1571 1572 1573 1574 1575 1576 1577 1578 1579 1580 1581 1582 1583 1584 1585 1586 1587 1588 1589 1590 1591 1592 1593 1594 1595 1596 1597 1598 1599 1600 1601 1602 1603 1604 1605 1606 1607 1608 1609 1610 1611 1612 1613 1614 1615 1616 1617 1618 1619 1620 1621 1622 1623 1624 1625 1626 1627 1628 1629 1630 1631 1632 1633 1634 1635 1636 1637 1638 1639 1640 1641 1642 1643 1644 1645 1646 1647 1648 1649 1650 1651 1652 1653 1654 1655 1656 1657 1658 1659 1660 1661 1662 1663 1664 1665 1666 1667 1668 1669 1670 1671 1672 1673 1674 1675 1676 1677 1678 1679 1680 1681 1682 1683 1684 1685 1686 1687 1688 1689 1690 1691 1692 1693 1694 1695 1696 1697 1698 1699 1700 1701 1702 1703 1704 1705 1706 1707 1708 1709 1710 1711 1712 1713 1714 1715 1716 1717 1718 1719 1720 1721 1722 1723 1724 1725 1726 1727 1728 1729 1730 1731 1732 1733 1734 1735 1736 1737 1738 1739 1740 1741 1742 1743 1744 1745 1746 1747 1748 1749 1750 1751 1752 1753 1754 1755 1756 1757 1758 1759 1760 1761 1762 1763 1764 1765 1766 1767 1768 1769 1770 1771 1772 1773 1774 1775 1776 1777 1778 1779 1780 1781 1782 1783 1784 1785 1786 1787 1788 1789 1790 1791 1792 1793 1794 1795 1796 1797 1798 1799 1800 1801 1802 1803 1804 1805 1806 1807 1808 1809 1810 1811 1812 1813 1814 1815 1816 1817 1818 1819 1820 1821 1822 1823 1824 1825 1826 1827 1828 1829 1830 1831 1832 1833 1834 1835 1836 1837 1838 1839 1840 1841 1842 1843 1844 1845 1846 1847 1848 1849 1850 1851 1852 1853 1854 1855 1856 1857 1858 1859 1860 1861 1862 1863 1864 1865 1866 1867 1868 1869 1870 1871 1872 1873 1874 1875 1876 1877 1878 1879 1880 1881 1882 1883 1884 1885 1886 1887 1888 1889 1890 1891 1892 1893 1894 1895 1896 1897 1898 1899 1900 1901 1902 1903 1904 1905 1906 1907 1908 1909 1910 1911 1912 1913 1914 1915 1916 1917 1918 1919 1920 1921 1922 1923 1924 1925 1926 1927 1928 1929 1930 1931 1932 1933 1934 1935 1936 1937 1938 1939 1940 1941 1942 1943 1944 1945 1946 1947 1948 1949 1950 1951 1952 1953 1954 1955 1956 1957 1958 1959 1960 1961 1962 1963 1964 1965 1966 1967 1968 1969 1970 1971 1972 1973 1974 1975 1976 1977 1978 1979 1980 1981 1982 1983 1984 1985 1986 1987 1988 1989 1990 1991 1992 1993 1994 1995 1996 1997 1998 1999 2000 2001 2002 2003 2004 2005 2006 2007 2008 2009 2010 2011 2012 2013 2014 2015 2016 2017 2018 2019 2020 2021 2022 2023 2024 2025 2026 2027 2028 2029 2030 2031 2032 2033 2034 2035 2036 2037 2038 2039 2040 2041 2042 2043 2044 2045 2046 2047 2048 2049 2050 2051 2052 2053 2054 2055 2056 2057 2058 2059 2060 2061 2062 2063 2064 2065 2066 2067 2068 2069 2070 2071 2072 2073 2074 2075 2076 2077 2078 2079 2080 2081 2082 2083 2084 2085 2086 2087 2088 2089 2090 2091 2092 2093 2094 2095 2096 2097 2098 2099 2100 2101 2102 2103 2104 2105 2106 2107 2108 2109 2110 2111 2112 2113 2114 2115 2116 2117 2118 2119 2120 2121 2122 2123 2124 2125 2126 2127 2128 2129 2130 2131 2132 2133 2134 2135 2136 2137 2138 2139 2140 2141 2142 2143 2144 2145 2146 2147 2148 2149 2150 2151 2152 2153 2154 2155 2156 2157 2158 2159 2160 2161 2162 2163 2164 2165 2166 2167 2168 2169 2170 2171 2172 2173 2174 2175 2176 2177 2178 2179 2180 2181 2182 2183 2184 2185 2186 2187 2188 2189 2190 2191 2192 2193 2194 2195 2196 2197 2198 2199 2200 2201 2202 2203 2204 2205 2206 2207 2208 2209 2210 2211 2212 2213 2214 2215 2216 2217 2218 2219 2220 2221 2222 2223 2224 2225 2226 2227 2228 2229 2230 2231 2232 2233 2234 2235 2236 2237 2238 2239 2240 2241 2242 2243 2244 2245 2246 2247 2248 2249 2250 2251 2252 2253 2254 2255 2256 2257 2258 2259 2260 2261 2262 2263 2264 2265 2266 2267 2268 2269 2270 2271 2272 2273 2274 2275 2276 2277 2278 2279 2280 2281 2282 2283 2284 2285 2286 2287 2288 2289 2290 2291 2292 2293 2294 2295 2296 2297 2298 2299 2300 2301 2302 2303 2304 2305 2306 2307 2308 2309 2310 2311 2312 2313 2314 2315 2316 2317 2318 2319 2320 2321 2322 2323 2324 2325 2326 2327 2328 2329 2330 2331 2332 2333 2334 2335 2336 2337 2338 2339 2340 2341 2342 2343 2344 2345 2346 2347 2348 2349 2350 2351 2352 2353 2354 2355 2356 2357 2358 2359 2360 2361 2362 2363 2364 2365 2366 2367 2368 2369 2370 2371 2372 2373 2374 2375 2376 2377 2378 2379 2380 2381 2382 2383 2384 2385 2386 2387 2388 2389 2390 2391 2392 2393 2394 2395 2396 2397 2398 2399 2400 2401 2402 2403 2404 2405 2406 2407 2408 2409 2410 2411 2412 2413 2414 2415 2416 2417 2418 2419 2420 2421 2422 2423 2424 2425 2426 2427 2428 2429 2430 2431 2432 2433 2434 2435 2436 2437 2438 2439 2440 2441 2442 2443 2444 2445 2446 2447 2448 2449 2450 2451 2452 2453 2454 2455 2456 2457 2458 2459 2460 2461 2462 2463 2464 2465 2466 2467 2468 2469 2470 2471 2472 2473 2474 2475 2476 2477 2478 2479 2480 2481 2482 2483 2484 2485 2486 2487 2488 2489 2490 2491 2492 2493 2494 2495 2496 2497 2498 2499 2500 2501 2502 2503 2504 2505 2506 2507 2508 2509 2510 2511 2512 2513 2514 2515 2516 2517 2518 2519 2520 2521 2522 2523 2524 2525 2526 2527 2528 2529 2530 2531 2532 2533 2534 2535 2536 2537 2538 2539 2540 2541 2542 2543 2544 2545 2546 2547 2548 2549 2550 2551 2552 2553 2554 2555 2556 2557 2558 2559 2560 2561 2562 2563 2564 2565 2566 2567 2568 2569 2570 2571 2572 2573 2574 2575 2576 2577 2578 2579 2580 2581 2582 2583 2584 2585 2586 2587 2588 2589 2590 2591 2592 2593 2594 2595 2596 2597 2598 2599 2600 2601 2602 2603 2604 2605 2606 2607 2608 2609 2610 2611 2612 2613 2614 2615 2616 2617 2618 2619 2620 2621 2622 2623 2624 2625 2626 2627 2628 2629 2630 2631 2632 2633 2634 2635 2636 2637 2638 2639 2640 2641 2642 2643 2644 2645 2646 2647 2648 2649